

1 JZ 61		Si-Br				B250C1500	8, 33	
1 K		Si-N	=BC 848B (SMD-Marking)	35	SOT-23			*BC 848
1 K		Si-N	=BC 848BW (SMD-Marking)	35(2mm)	SOT-323			*BC 848W
1 K		Si-N	=MMBT 6428 (SMD-Marking)	35	SOT-23			*MMBT 6428
1 K 34(A)		Ge-Di	=1N34	31a		AA 133	31a	*1N34
1 K 60		Ge-Di	=1N60	31a		AA 138	31a	*1N60
1 K 90		Ge-Di	=1N90	31a		AA 138	31a	*1N90
1 K 261		Ge-Di		31a		AA 138	31a	
1 KP		N-FET	=2SK316-P (SMD-Marking)	35	SOT-23			*2SK316
1 Kp		Si-N	=BCV 61B (SMD-Marking)	44	SOT-143			*BCV 61
1 KQ		N-FET	=2SK316-Q (SMD-Marking)	35	SOT-23			*2SK316
1 KR		Si-N	=2SD2210-R (SMD-Marking)	39	SOT-89			*2SD2210
1 KR		Si-N	=BC 848BR (SMD-Marking)	35	SOT-23			*BC 848R
1 KS		Si-N	=2SD2210-S (SMD-Marking)	39	SOT-89			*2SD2210
1 Ks		Si-N	=BCV 61B (SMD-Marking)	44	SOT-143			*BCV 61
1 KT		Si-N	=2SD2210-T (SMD-Marking)	39	SOT-89			*2SD2210
1 L		Si-P	=2SB1537 (SMD-Marking)	39	SOT-89			*2SB1537
1 L(p,s)		Si-N	=BC 848C (SMD-Marking)	35	SOT-23			*BC 848
1 L		Si-N	=BC 848CW (SMD-Marking)	35(2mm)	SOT-323			*BC 848W
1 L		Si-N	=MMBT 6429 (SMD-Marking)	35	SOT-23			*MMBT 6429
1 LM		Si-N	=2SC4103-M (SMD-Marking)	35(2mm)	SOT-323			*2SC4103
1 LN		Si-N	=2SC4103-N (SMD-Marking)	35(2mm)	SOT-323			*2SC4103
1 LP		Si-N	=2SC4103-P (SMD-Marking)	35(2mm)	SOT-323			*2SC4103
1 Lp		Si-N	=BCV 61C (SMD-Marking)	44	SOT-143			*BCV 61
1 LQ		Si-N	=2SC4103-Q (SMD-Marking)	35(2mm)	SOT-323			*2SC4103
1 LR		Si-N	=BC 848CR (SMD-Marking)	35	SOT-23			*BC 848R
1 Ls		Si-N	=BCV 61C (SMD-Marking)	44	SOT-143			*BCV 61
1 M		Si-N	=2SD2357 (SMD-Marking)	39	SOT-89			*2SD2357
1 M(p)		Si-N	=BC 848 (SMD-Marking)	35	SOT-23			*BC 848
1 M		Si-N	=BC 848W (SMD-Marking)	35(2mm)	SOT-323			*BC 848W
1 M		Si-N	=FMMT-A13 (SMD-Marking)	35	SOT-23			*FMMT-A13
1 M		Si-N	=IMBT 3903 (SMD-Marking)	35	SOT-23			*IMBT 3903
1 M		Si-N	=MMBTA 13 (SMD-Marking)	35	SOT-23			*MMBTA 13
1 M 3.3...200ZS	Mot	Z-Di	3,3...200V, 2,5W, ±20%	31a	DO-41			BZD23/... BZT03/... BZX70/...
1 M ...ZS5		Z-Di	±5%	31a	DO-41			BZD23/... BZT03/... BZX70/...
1 M ...ZS10		Z-Di	±10%	31a				BZD23/... BZT03/... BZX70/...
1 MN		Si-N	=2SC4128-N (SMD-Marking)	35(2mm)	SOT-323			*2SC4128
1 MP		Si-N	=2SC4128-P (SMD-Marking)	35(2mm)	SOT-323			*2SC4128
1 MP		Si-P	=2SJ84-P (SMD-Marking)	35	SOT-23			*2SJ84
1 Mp		Si-N	=BCV 61 (SMD-Marking)	44	SOT-143			*BCV 61
1 MQ		Si-P	=2SJ84-Q (SMD-Marking)	35	SOT-23			*2SJ84
1 MR		Si-P	=2SJ84-R (SMD-Marking)	35	SOT-23			*2SJ84
1N								
1 N		Si-P	=2SB1539 (SMD-Marking)	39	SOT-89			*2SB1539
1 N		Si-N	=FMMT-A14 (SMD-Marking)	35	SOT-23			*FMMT-A14
1 N		Si-N	=IMBT 3904 (SMD-Marking)	35	SOT-23			*IMBT 3904
1 N		Si-N	=MMBTA 14 (SMD-Marking)	35	SOT-23			*MMBTA 14
1 N 21	Nec,Tho,++	Si-Di	UHF, S-Band Mx	Koax	SOD-47			-
1 N 22	Nec	Si-Di	UHF, X-Band Dem	Koax	SOD-48			-
1 N 23	Nec,Tho,++	Si-Di	UHF, X-Band Mx	Koax	SOD-47			-
1 N 25	USA	Si-Di	UHF, L-Band Mx	Koax	SOD-47			-
1 N 26	USA	Si-Di	UHF, K-Band Mx	Koax	SOD-49			-
1 N 28	Nec	Si-Di	UHF, S-Band Dem	Koax	SOD-47			-
1 N 31(A)	USA	Si-Di	UHF, X-Band Dem	Koax	SOD-49			-
1 N 32(A)	USA	Si-Di	UHF, S-Band Dem	Koax	SOD-47			-
1 N 34(A)	EUR,USA,Nec	Ge-Di	Uni, Dem, 75V, 50mA	31a	DO-7	AA 133	31a	AA 113, 1N60
1 N 35	USA,Nec,Tho	Ge-Di	FM Dem, Matched Pair, 75V, 22,5mA	2x 31a	2x DO-7			AA 113, 1N34
1 N 36	Kem,Sem,Tho	Ge-Di	HF Dem, 36V, 16mA	31a	DO-7			AA 113, AA 119, 1N34, 1N60
1 N 38	USA,Nec,Tho	Ge-Di	Uni, 120V, 50mA	31a	DO-7			AA 117...118, AA 132...133
1 N 39	USA,Nec,Tho	Ge-Di	Uni, 200V, 50mA	31a	DO-7			-
1 N 40	Kem,Spe	Ge-Di	4x HF Dem, Matched Pair, 25V, 225mA	4x 31a	4x DO-7			-
1 N 41	Kem,Spe	Ge-Di	4x HF Dem, Matched Quart., 32V					-
1 N 42	Kem,Spe	Ge-Di	4x Uni, 115V, 0,1A(ss)	4x 31a	4x DO-7			AA 117...118, AA 132...133
1 N 43	USA,Tho	Ge-Di	Uni, 70V, 40mA	31a	DO-7			AA 117...118, AA 132...134, 1N34, 1N54
1 N 44	USA	Ge-Di	Uni, 115V, 35mA	31a	DO-7			AA 117...118, AA 132...134, 1N34, 1N54
1 N 44 A1	Tos	Si-Di	KV-Rr, 13kV, 0,67A					-
1 N 45	USA	Ge-Di	HF, Uni, 75V, 35mA	31a	DO-7			AA 113, AA 117...118, 1N34, 1N60
1 N 46	USA	Ge-Di	Uni, 80V, 40mA	31a	DO-7			AA 117...118, AA 132...134, 1N34, 1N54
1 N 47	USA	Ge-Di	Uni, 150V, 30mA	31a	DO-7			AA 133, 1N39
1 N 48	USA,Tho	Ge-Di	Uni, 80V, 50mA	31a	DO-7			AA 117...118, AA 132...133
1 N 49	USA,Tho	Ge-Di	Uni, 75V	31a	DO-7			AA 117...118, AA 132...133, 1N34, 1N54
1 N 50	USA,Tho	Ge-Di	Uni, 75V	31a	DO-7			AA 117...118, AA 132...133, 1N34, 1N54
1 N 51	USA,Tho	Ge-Di	Dem, Uni, 46V, 30mA	31a	DO-7			AA 113, 1N34, 1N54, 1N60
1 N 52(A)	USA,Tho	Ge-Di	Uni, 80V, 50mA	31a	DO-7			AA 117...118, AA 132...133
1 N 52 A1	Tos	Si-Di	=1N44A1: 15kV					-
1 N 53	USA	Si-Di	UHF, Ka-Band Mx	Koax	SOD-49			-
1 N 54(A)	USA,Nec,Tho	Ge-Di	Uni, 75V, 50mA	31a	DO-7	AA 133	31a	AA 113, AA 117...118, 1N34
1 N 55(A,B)	USA,Tho	Ge-Di	Uni, 150...180V, 30...50mA	31a	DO-7			-
1 N 56(A)	USA,Tho	Ge-Di	Uni, 50V, 60mA	31a	DO-7			AA 117...118, AA 132...134, 1N60
1 N 57(A)	USA,Tho	Ge-Di	Uni, 80V, 40mA	31a	DO-7			AA 117...118, AA 132...133
1 N 58(A)	USA,Nec,Tho	Ge-Di	Uni, 115V, 50mA	31a	DO-7			AA 117...118, AA 132...133
1 N 59	Idc	Ge-Di	Uni, 280V, 50mA	31a	DO-7			-
1 N 60(A)	USA,EUR,JAP	Ge-Di	AM/FM Dem, TV IF Dem, 50V, 50mA	31a	DO-7	AA 138	31a	AA 113, AA 138, 1N34, 1N54
1 N 61	USA	Ge-Di	Uni, 140V, 40mA	31a	DO-7			AA 133, 1N39
1 N 61 A1	Tos	Si-Di	=1N44A1: 30kV					-
1 N 62	USA	Ge-Di	Uni, 140V, 40mA	31a	DO-7			AA 133, 1N39
1 N 63(A)	USA,Tho	Ge-Di	Uni, 100V, 30...50mA	31a	DO-7			AA 117...118, AA 132...133
1 N 64(A)	USA,Tho	Ge-Di	Uni, 25V, 50mA	31a	DO-7			AA 113, AA 119, 1N34, 1N54, 1N60, ++
1 N 65	USA,Tho	Ge-Di	HF Dem, 70V, 50mA	31a	DO-7			AA 113, 1N34, 1N54, 1N60
1 N 66	USA,Tho	Ge-Di	Uni, 60V, 50mA	31a	DO-7			AA 117...118, AA 132...134, 1N60, ++
1 N 67(A)	USA,Tho	Ge-Di	Dem, Uni, 92V, 35mA	31a	DO-7			AA 113, AA 119, 1N34, 1N54, 1N60, ++
1 N 68(A)	USA,Tho	Ge-Di	Uni, 100V, 35mA	31a	DO-7			AA 117...118, AA 132...133

PDF .Support