

2 N 6525	Mws	Si-N	HF P, 40V, 2.5A, 20W	62a	-	-	-	-	-	-	-
2 N 6526	Mws	Si-N	HF P, 50V, 0.5A, 3.9W	62a	-	-	-	-	-	-	-
2 N 6527	Mws	Si-N	HF P, 50V, 1A, 5W	62a	-	-	-	-	-	-	-
2 N 6528	Mws	Si-N	HF P, 50V, 1.2A, 10W	62a	-	-	-	-	-	-	-
2 N 6529	Mws	Si-N	HF P, 50V, 2.5A, 20W	62a	-	-	-	-	-	-	-
2 N 6530	Rca	Si-N-Darl+Di	LFS P, 80/80V, 8/15A, 65W, >20MHz, hFE=1k...10k	17j	TO-220	-	-	-	-	BD 647, BD 899, BDX 53B, BDX 73B, ++	-
2 N 6531	Rca	Si-N-Darl+Di	LFS P, 100/100V, 8/15A, 65W, hFE=500...5k	17j	TO-220	-	-	-	-	BD 649, BD 901, BDX 53C, BDX 73C, ++	-
2 N 6532	Rca	Si-N-Darl+Di	LFS P, 100/100V, 8/15A, 65W, hFE=1k...10k	17j	TO-220	-	-	-	-	BD 649, BD 901, BDX 53C, BDX 73C, ++	-
2 N 6533	Rca	Si-N-Darl+Di	LFS P, 120/120V, 8/15A, 65W, hFE=1k...10k	17j	TO-220	-	-	-	-	BD 651, BDT 21, BDX 53D, BDX 73D, ++	-
2 N 6534	Rca	Si-N-Darl+Di	=2N6530: 36W	22a	TO-66	-	-	-	-	>2N6530	-
2 N 6535	Rca	Si-N-Darl+Di	=2N6531: 36W	22a	TO-66	-	-	-	-	>2N6531	-
2 N 6536	Rca	Si-N-Darl+Di	=2N6532: 36W	22a	TO-66	-	-	-	-	>2N6532	-
2 N 6537	Rca	Si-N-Darl+Di	=2N6533: 36W	22a	TO-66	-	-	-	-	>2N6532	-
2 N 6538	Tix	Si-N	Uni, In, 60/40V, 0.2A, 0.625W, >200MHz, hFE>100	7e	TO-92	-	-	-	-	BC 414, BC 550, 2SC2240, 2SC2459, ++	-
2 N 6539	Si-N	=2N6538: hFE>250	7e	TO-92	-	-	-	-	-	BC 414, BC 550, 2SC2240, 2SC2459, ++	-
2 N 6540	Si-N	=2N6538: 80/60V, hFE>100	7e	-	-	-	-	-	-	2SC1775(A), 2SC2240, 2SC2459, 2SC2390, ++	-
2 N 6541	Si-N	=2N6538: 80/65V, hFE>60	7e	TO-92	-	-	-	-	-	2SC1775(A), 2SC2240, 2SC2459, 2SC2390, ++	-
2 N 6542	USA, Mot, Rca Sgs, Tix, Tos	Si-N	S P, 650/300V, 5/10A, 100W, >6MHz, <750/4800ns	23a	TO-3	-	-	-	-	BUS 11(A), BUX 82...83, 2SC3048, ++	-
2 N 6543	Si-N	=2N6542: 850/400V	23a	TO-3	-	-	-	-	-	BUS 11(A), BUX 82...83, 2SC3048, ++	-
2 N 6544	=2N6542	Si-N	S P, 650/300V, 8/16A, 125W, >6MHz, <1050/5000ns	23a	TO-3	-	-	-	-	BUS 12(A), BUX 47(A), 2SC3092, 2SD811, ++	-
2 N 6545	Si-N	=2N6544: 850/400V	23a	TO-3	-	-	-	-	-	BUS 12(A), BUX 47(A), 2SC3092, 2SD811, ++	-
2 N 6546	=2N6542	Si-N	S P, 650/300V, 15/30A, 175W, >6MHz, <1050/5000ns	23a	TO-3	-	-	-	-	BUS 13(A), BUS 97(A), BUX 47(A...C), ++	-
2 N 6547	Si-N	=2N6546: 850/400V	23a	TO-3	-	-	-	-	-	BUS 13(A), BUS 97(A), BUX 47(A...C), ++	-
2 N 6548	Mot, Nsc	Si-N-Darl	LFS P, 50/40V, 2A, 10W, hFE=25k...150k	13m	TO-202	-	-	-	-	BD 411...412, MPS-U45	-
2 N 6549	Si-N-Darl	=2N6548: hFE=15k...150k	13m	TO-202	-	-	-	-	-	BD 411...412, MPS-U45	-
2 N 6550	Tdy	N-FET	Uni, 20V, Idss=10...250mA, Up<3V	2f	TO-46	-	-	-	-	-	-
2 N 6551	Mot, Nsc	Si-N	LFS P, 60/60V, 1/2A, 10W, >75MHz	{2N6554 13m	TO-202	(2SC4135)4	30j	-	-	BC 366, BD 415, BD 517, BD 525, ++	-
2 N 6552	Si-N	=2N6551: 80/80V	{2N6555 13m	TO-202	(2SC4135)4	30j	-	-	-	BC 367, BD 417, BD 519, BD 527, ++	-
2 N 6553	Si-N	=2N6551: 100/100V	{2N6556 13m	TO-202	(2SC4135)4	30j	-	-	-	BD 419, BD 529	-
2 N 6554	Mot, Nsc	Si-P	LFS P, 60/60V, 1/2A, 10W, >75MHz	{2N6551 13m	TO-202	(2SA1593)4	30j	-	-	BC 363, BD 416, BD 518, BD 526, ++	-
2 N 6555	Si-P	=2N6554: 80/80V	{2N6552 13m	TO-202	(2SA1593)4	30j	-	-	-	BC 364, BD 418, BD 520, BD 528, ++	-
2 N 6556	Si-P	=2N6554: 100/100V	{2N6553 13m	TO-202	(2SA1593)4	30j	-	-	-	BD 420, BD 530	-
2 N 6557	Mot	Si-N	Vid P, 250/250V, 0.5/0.7A, 10W, >45MHz	13m	TO-202	-	-	-	-	BF 381...382, BF 460...462, MPS-U10	-
2 N 6558	Si-N	=2N6557: 300/300V	13m	TO-202	-	-	-	-	-	BF 382, BF 461...462, BF 468, MPS-U10	-
2 N 6559	Si-N	=2N6557: 350/350V	13m	TO-202	-	-	-	-	-	BF 462	-
2 N 6560	Sol, Stc	Si-N	S P, 450/450V, 10A, 220W, >10MHz, <600/3000ns	23a	TO-3	-	-	-	-	-	-
2 N 6561	Si-N	=2N6560: 300/300V, >15MHz, <600/1700ns	23a	TO-3	-	-	-	-	-	-	-
2 N 6562	Si-N	=2N6560: 175W	49a	TO-61	-	-	-	-	-	2N6689...93	-
2 N 6563	Si-N	=2N6561: 175W	49a	TO-61	-	-	-	-	-	2N6689...93	-
2 N 6564	Gen, Tag	50Hz-Thy	300V, 0.5A(Tc=55°), 0.8A-, Igt/Ih<0.2/<5mA	7n	TO-92	BRX 49	7a	-	-	2N5064, TAG 72D, TAG 59D, 2N6683, ++	-
2 N 6565	50Hz-Thy	=2N6564: 400V	7n	TO-92	BRX 49	7a	-	-	-	TAG 72D, TAG 59D, 2N6683, (BT 149D,++)5	-
2 N 6566	Tdy	Si-N	S, Chopper, 30/30/30V, 0.1A, 0.4W, <300/150ns	2a	TO-46	-	-	-	-	-	-
2 N 6567	Tdy	Si-P	S, Chopper, 30/30/30V, 0.1A, 0.4W, <300/150ns	2a	TO-46	-	-	-	-	-	-
2 N 6568	Tdy	N-FET	Uni, 30V, Idss>500mA, Up<10V	2b	TO-18	-	-	-	-	-	-
2 N 6569	Fch, Mot, Rca Tix	Si-N	LFS P, 45/40V, 12/24A, 100W, >1.5MHz, <1.9/6.5µs	23a	TO-3	-	-	-	-	BD 315, BD 545A, BDW 51, 2N5881...82, ++	-
2 N 6570	Si-N	=2N6569: 12/24A, 100W, >1.5MHz, <1.9/6.5µs	{2N6594 23a	TO-3	-	-	-	-	-	-	-
2 N 6571	Ste, Trw	Si-N	LFS P, 100/90V, 40A, 250W, >1MHz	23a	TO-3	-	-	-	-	2N6032...33, 2N6274...77	-
2 N 6572	Si-N	=2N6570: 115/105V	23a	TO-3	-	-	-	-	-	2N6032...33, 2N6274...77	-
2 N 6573	Ctr	Si-N	HF P, 60/30V, 12A, 250W	57s	SOT-119	-	-	-	-	-	-
2 N 6574	USA, Mot, Tho	Si-N	S P, 500/250V, 10/15A, 125W, 15MHz, 1050/3200ns	23a	TO-3	-	-	-	-	BUW 25...26, BUW 34...36, 2SC3046, ++	-
2 N 6575	Si-N	=2N6573: 600/275V	23a	TO-3	-	-	-	-	-	BUW 25...26, BUW 34...36, 2SC3046, ++	-
2 N 6576	Lbd, Mot, Rca	Si-N-Darl+Di	LFS P, 60/60V, 15/30A, 120W, >4MHz, hFE=500...5k	23a	TO-3	-	-	-	-	BUS 12(A), BUW 26, BUW 35...36, 2SC3046++	-
2 N 6577	Si-N-Darl+Di	=2N6576: 90/90V	23a	TO-3	-	-	-	-	-	BDV 67, BDW 83A, BDX 67, MJ 4033, ++	-
2 N 6578	Si-N-Darl+Di	=2N6576: 120/120V	23a	TO-3	-	-	-	-	-	BDV 67A, BDW 83C, BDX 67B, MJ 4035, ++	-
2 N 6579	Amc	Si-N	S P, 450/350V, 10A, 125W, >25MHz, <550/2500ns	23a	TO-3	-	-	-	-	BDV 67B, BDW 83D, BDX 67C	-
2 N 6580	Si-N	=2N6579: 500/400V	23a	TO-3	-	-	-	-	-	BUW 24...26, BUW 34...36, 2SC3046, ++	-
2 N 6581	Si-N	=2N6579: 550/450V	23a	TO-3	-	-	-	-	-	BUW 25...26, BUW 34...36, 2SC3046, ++	-
2 N 6582	Amc, Trw	Si-N	S-L, 450/350V, 10A, 125W, >25MHz, <550/2500ns	23a	TO-3	-	-	-	-	BUW 24...26, BUW 34...36, 2SC3046, ++	-
2 N 6583	Si-N	=2N6582: 500/400V	23a	TO-3	-	-	-	-	-	BUW 25...26, BUW 34...36, 2SC3046, ++	-
2 N 6584	Si-N	=2N6582: 550/450V	23a	TO-3	-	-	-	-	-	BUW 25...26, BUW 35...36, 2SC3046, ++	-
2 N 6585	Si-N	=2N6579:	49a	TO-61	-	-	-	-	-	2N6689...93	-
2 N 6586	Si-N	=2N6580:	49a	TO-61	-	-	-	-	-	2N6690, 2N6692...93	-
2 N 6587	Si-N	=2N6581:	49a	TO-61	-	-	-	-	-	2N6690, 2N6692...93	-
2 N 6588	Si-N	=2N6582:	49a	TO-61	-	-	-	-	-	2N6689...93	-
2 N 6589	Si-N	=2N6583:	49a	TO-61	-	-	-	-	-	2N6690, 2N6692...93	-
2 N 6590	Si-N	=2N6584:	49a	TO-61	-	-	-	-	-	2N6690, 2N6692...93	-
2 N 6591	Mot, Nsc	Si-N	S, HA Drv, Reg, 150/150V, 0.5/1A, 10W, >35MHz	13m	TO-202	-	-	-	-	BF 380...382, BF 460...462, MPS-U10, ++	-
2 N 6592	Si-N	=2N6591: 200/200V	13m	TO-202	-	-	-	-	-	BF 381...382, BF 460...462, MPS-U10, ++	-
2 N 6593	Si-N	=2N6591: 250/250V	13m	TO-202	-	-	-	-	-	BF 381...382, BF 460...462, MPS-U10, ++	-
2 N 6594	Mot, Rca	Si-P	LFS P, 45/40V, 12/24A, 100W, >2.5MHz, <1.9/6.5µs	23a	TO-3	-	-	-	-	BD 316, BD 546A, BDW 52, 2N5879...80, ++	-
2 N 6595	Amp	Si-N	UHF, In, 20V, 25mA, 0.2W, >3.5GHz	5g	TO-72	-	-	-	-	BFQ 22, BFQ 53, BFT 66...67	-
2 N 6596	Amp	Si-N	UHF, In, 15V, 25mA, 0.2W, >3.5GHz	5g	TO-72	-	-	-	-	BFQ 22, BFQ 53, BFT 66...67	-
2 N 6597	Amp	Si-N	UHF, In, 20V, 25mA, 0.2W, >4GHz	5g	TO-72	-	-	-	-	BFQ 22, BFQ 53, BFT 66...67	-
2 N 6598	Amp	Si-N	UHF, In, 15V, 25mA, 0.2W, >4GHz	5g	TO-72	-	-	-	-	BFQ 22, BFQ 53, BFT 66...67	-
2 N 6599	Amp	Si-N	UHF, In, 20V, 75mA, 0.5W, >3GHz	5g	TO-72	-	-	-	-	BFQ 63, 2SC2570, 2SC3037, 2SC3337	-
2 N 6600	Amp	Si-N	UHF, In, 20V, 75mA, 0.3W, >3.5GHz	5g	TO-72	-	-	-	-	BFQ 63, 2SC2570, 2SC3037, 2SC3337	-
2 N 6601	Amp	Si-N	UHF, In, 20V, 50mA, 0.25W, >1GHz	5g	TO-72	-	-	-	-	BFQ 63, BFS 55, 2SC2498	-
2 N 6602	Mot	Si-N	UHF, -/15V, 25mA, >3.5GHz	52r	SOT-100	-	-	-	-	BFQ 59...60, BFQ 72, BFT 65, 2SC2844, ++	-
2 N 6603	Mot	Si-N	UHF, 25V, 30mA, >3.5GHz	52r	SOT-100	-	-	-	-	BFQ 59...60, BFQ 72, BFT 65, 2SC2844, ++	-
2 N 6604	Mot	Si-N	UHF, 25V, 50mA, >3.5GHz	52r	SOT-100	-	-	-	-	BFQ 72, BFT 65, 2SC2844	-
2 N 6605	Mot, Tag	50Hz-Thy	30V, 0.275A(Ta=55°), Igt/Ih<0.2/<5mA	2a	TO-18	(TAG 103 X)6	2a	-	-	TAG 06Y, (TIC 44, TIC 60, MCR 100-3,++)6	-
2 N 6606	50Hz-Thy	=2N6605: 60V	2a	TO-18	(BRX 49)6	7a	-	-	-	TAG 06Y, (TIC 46, TIC 62, MCR 100-3,++)6	-
2 N 6607	50Hz-Thy	=2N6605: 100V	2a	TO-18	(BRX 49)6	7a	-	-	-	TAG 06A, (TIC 46, TIC 62, MCR 100-3,++)6	-
2 N 6608	50Hz-Thy	=2N6605: 200V	2a	TO-18	(BRX 49)6	7a	-	-	-	TAG 06B, (TIC 47, TIC 64, MCR 100-4,++)6	-
2 N 6609	Mot, Rca	Si-P	LFS P, 160/140V, 16A, 150W, >2MHz	{2N3773 23a	TO-3	-	-	-	-	BD 746F, MJ 15016, 2SA1117	-
2 N 6617	Hew	Si-N	UHF, -/16V, 10mA, 0.15W, 8GHz	51r	SOT-173	-	-	-	-	BFQ 33, BFQ 77, 2SC1948	-
2 N 6618	Hew, Mot	Si-N	UHF, 35V, 20mA, 0.3W(TG=125), 8GHz	51r	SOT-100	-	-	-	-	BFQ 33, BFQ 77, 2SC1948	-
2 N 6619	Sie	Si-N	=BFR 35A	-	-	-	-	-	-	>BFR 35A	-
2 N 6620	Sie	Si-N	=BFR 34A	-	-	-	-	-	-	>BFR 34A	-
2 N 6621	Sie	Si-N	=BFW 92	-	-	-	-	-	-	>BFW 92	-