

| | | | | | | |
|--------------|--------------------------------|----------|--|-------|------------|--|
| 2 N 4437 | | Si-N | =2N4436: hFE=100...220 | 8a | TO-106 | BC 337A, BC 637, BSV 59, 2N2221...22(A), ++ |
| 2 N 4438 | Sca, Ssi, Sty | Si-N | Vid, 300/300V, 0.2A, 1W, >30MHz, hFE=40...120 | 2a | TO-39 | BF 259, BF 659, BFR 59, BFS 89, 2N5058 |
| 2 N 4439 | | Si-N | =2N4438: hFE=100...240 | 2a | TO-39 | BF 259, BF 659, BFR 59, BFS 89, 2N5058 |
| 2 N 4440 | USA, Rca, Mot Tho, Tix, ++ | Si-N | VHF/UHF P, 65/40V, 1.5A, PQ<5W(400MHz) | 49a | TO-60 | - |
| 2 N 4441 | Mot | 50Hz-Thy | 50V, 5.1A(Tc=73°), 8A=, Igt/Ih<30/<40mA | 16e | TO-127 | - |
| 2 N 4442 | | 50Hz-Thy | =2N4441: 200V | 16e | TO-127 | - |
| 2 N 4443 | | 50Hz-Thy | =2N4441: 400V | 16e | TO-127 | - |
| 2 N 4444 | | 50Hz-Thy | =2N4441: 600V | 16e | TO-127 | - |
| 2 N 4445 | Tix, Tdy | N-FET | S, Chopper, 25V, 0.4A, Up<10V | 2b | TO-46 | - |
| 2 N 4445 A | | N-FET | =2N4445: 35V | 2b | TO-46 | - |
| 2 N 4446 | Tix, Tdy | N-FET | S, Chopper, 25V, 0.4A, Up<5V | 2b | TO-46 | - |
| 2 N 4446 A | | N-FET | =2N4446: 35V | 2b | TO-46 | - |
| 2 N 4447 | Tix, Tdy | N-FET | S, Chopper, 20V, 0.4A, Up<5V | 2b | TO-46 | - |
| 2 N 4447 A | | N-FET | =2N4447: 25V | 2b | TO-46 | - |
| 2 N 4448 | Tix, Tdy | N-FET | S, Chopper, 20V, 0.4A, Up<5V | 2b | TO-46 | - |
| 2 N 4448 A | | N-FET | =2N4448: 25V | 2b | TO-46 | - |
| 2 N 4449 | Fch, Ray, Sca | Si-N | S, -15V, 0.2A, 0.3W, >500MHz, <69/20ns | 2a | TO-46 | BSS 11...12, BSX 19...20, 2N2368...69(A), ++ |
| 2 N 4450 | Fch, Mot, Sgs | Si-N | Uni, 60/30V, 0.5A, 0.36W, 350MHz, 50/125ns | 2a | TO-46 | BC 337A, BC 637, BSV 59, 2N2221...22(A), ++ |
| 2 N 4451 | Fch, Sgs | Si-P | S, -12V, 0.1A, 0.3W, >400MHz, <65/95ns | 2a | TO-46 | BSX 36, 2N4313, 2N3209, 2N4125...26, ++ |
| 2 N 4452 | Fch, Sca, Sgs | Si-P | S, 45/45V, 0.6A, 0.35W, >200MHz, <95/210ns | 2a | TO-46 | BC 327, BC 638, BSW 24, 2N2906...07(A), ++ |
| 2 N 4453 | Fch, Mot, Sgs | Si-P | Uni, 25/18V, 0.2A, 0.3W, >400MHz, 30/60ns | 2a | TO-46 | BC 308, BC 558, BSW 24, 2N3250...51(A), ++ |
| 2 N 4576 | | Si-N | S P, 100V, 150W | | | - |
| 2 N 4851 | Mot, Tix | UJT-P | 35/30V, 50mA, iEM=1.5A, 0.3W, Ip<2µA, Iv>2mA, η=0.56...0.75, Rbb=4.7...9.1kΩ | 5e | TO-72 | 2N4947, 2N4948, 2N4893 |
| 2 N 4852 | | UJT-P | =2N4851: Iv>4mA, η=0.7...0.85 | 5e | TO-72 | 2N4892 |
| 2 N 4853 | | UJT-P | =2N4851: Ip<0.4µA, Iv>6mA, η=0.7...0.85 | 5e | TO-72 | - |
| 2 N 4854 | Mot, Sgs, Tix | Si-N/P | NPN+PNP, 60/40V, 0.6A, 0.6W, >200MHz, hFE=100...300 | TO-77 | (CBE-EBC-) | BFX 79 |
| 2 N 4855 | | Si-N/P | =2N4854: hFE=40...120 | TO-77 | (CBE-EBC-) | BFX 79 |
| 2 N 4856(A) | USA, EUR | N-FET | S, sym, 40V, Idss>50mA, Up<10V | 2b | TO-18 | BFS 74, BFS 77, BSV 78, 2N3970, 2N4391 |
| 2 N 4857(A) | USA, EUR | N-FET | S, sym, 40V, Idss>20mA, Up<6V | 2b | TO-18 | BFS 75, BFS 78, BSV 79 |
| 2 N 4858(A) | USA, EUR | N-FET | S, sym, 40V, Idss>8mA, Up<4V | 2b | TO-18 | BFS 76, BFS 79, BSV 80, 2N4093 |
| 2 N 4859(A) | USA, EUR | N-FET | S, sym, 30V, Idss>50mA, Up<10V | 2b | TO-18 | BFS 74, BFS 77, BSV 78, 2N3970, 2N4391 |
| 2 N 4860(A) | USA, EUR | N-FET | S, sym, 30V, Idss>20mA, Up<6V | 2b | TO-18 | BFS 75, BFS 78, BSV 79 |
| 2 N 4861(A) | USA, EUR | N-FET | S, sym, 30V, Idss>8mA, Up<4V | 2b | TO-18 | BFS 76, BFS 79, BSV 80, 2N4093 |
| 2 N 4862 | USA | Si-N | LFS, 140/120V, 2A, 4W(Tc=100°), >50MHz | 2a | TO-46 | (BUX 49, BUY 41, 2SC1860)ᶠ |
| 2 N 4863 | USA | Si-N | LFS, 140/120V, 2A, 7W(Tc=25°), >50MHz | 2a | TO-5 | (BUX 49, BUY 41, 2SC1860)ᶠ |
| 2 N 4864 | USA | Si-N | LFS P, 140/120V, 2A, 29W, >50MHz | 22a | TO-66 | 2SC2529, 2SC2660, 2SD759...760 |
| 2 N 4865 | USA | Si-N | S P, 100/80V, 90A, 350W, >10MHz | 49m | TO-114 | 2N6309...11 |
| 2 N 4866 | | Si-N | =2N4865: 140/120V | 49m | TO-114 | 2N6309...11 |
| 2 N 4867(A) | Isi, Tix, ++ | N-FET | Uni, In, 40V, Idss>0.4mA, Up<2V | 5k | TO-72 | 2N4339, 2N5358, 2SK83, 2SK193, 2SK195 |
| 2 N 4868(A) | Isi, Tix, ++ | N-FET | Uni, In, 40V, Idss>3mA, Up<3V | 5k | TO-72 | BC 264, BF 410, 2SK192, 2SK370 |
| 2 N 4869(A) | Isi, Tix | N-FET | Uni, In, 40V, Idss>2.5mA, Up<6V | 5k | TO-72 | BF 256, BFS 71, 2N3822, 2N4221, ++ |
| 2 N 4870 | Mot, Phi | UJT-P | 35/30V, 50mA, iEM=1.5A, 0.3W, Ip<5µA, Iv>2mA, η=0.56...0.75, Rbb=4...9.1kΩ | 7b | TO-92 | 2N4891 |
| 2 N 4871 | | UJT-P | =2N4870: Iv>4mA, η=0.7...0.85 | 7b | TO-92 | 2N2646 |
| 2 N 4872 | Fch, Sgs | Si-P | S, RadH, 12/12V, 0.05A, 0.3W, >900MHz, <25/30ns | 2a | TO-18 | - |
| 2 N 4873 | Fch, Sgs | Si-N | S, RadH, 40/15V, 0.2A, 0.36W, >700MHz, <20/30ns | 2a | TO-18 | - |
| 2 N 4874 | Ray, Sca, Tix | Si-N | VHF/UHF Os, Drv, 30V, 0.2A, 0.72W, >900MHz | 2a | TO-39 | BFR 36, 2SC1199, 2SC1252, 2SC1365...66 |
| 2 N 4875 | Ray, Sca, Tix | Si-N | VHF/UHF Os, Drv, 40V, 0.2A, 0.72W, >800MHz | 2a | TO-39 | BFR 36, 2SC1199, 2SC1252, 2SC1365...66 |
| 2 N 4876 | Ray, Sca, Tix | Si-N | VHF/UHF Os, Drv, 40V, 0.2A, 0.72W, >650MHz | 2a | TO-39 | BFR 36, 2SC1199, 2SC1252, 2SC1365...66 |
| 2 N 4877 | USA, Mot | Si-N | LFS, 70/60V, 4A, 10W(Tc=25°), >30MHz | 2a | TO-39 | BUX 34, BUY 80, 2N5336...39 |
| 2 N 4878 | Isi, Sol, Sty | Si-N | =2N4044: 0.5W | TO-71 | (CBE-EBC-) | >2N4044 |
| 2 N 4879 | Isi, Sol, Sty | Si-N | =2N4100: 0.5W | TO-71 | (CBE-EBC-) | >2N4100 |
| 2 N 4880 | Isi, Sol, Sty | Si-N | =2N4045: 0.5W | TO-71 | (CBE-EBC-) | >2N4045 |
| 2 N 4881 | Tdy, Tix, Tsc | N-FET | S, 300V, Idss>0.4mA, Up<15V | 2b | TO-5 | 2N5543 |
| 2 N 4882 | Tdy, Tix, Tsc | N-FET | S, 300V, Idss>1.5mA, Up<15V | 2b | TO-5 | 2N5543 |
| 2 N 4883 | Tdy, Tix, Tsc | N-FET | S, 200V, Idss>0.4mA, Up<15V | 2b | TO-5 | 2N5542...43 |
| 2 N 4884 | Tdy, Tix, Tsc | N-FET | S, 200V, Idss>1.5mA, Up<15V | 2b | TO-5 | 2N5542...43 |
| 2 N 4885 | Tdy, Tix, Tsc | N-FET | S, 125V, Idss>0.4mA, Up<15V | 2b | TO-5 | 2N5542...43 |
| 2 N 4886 | Tdy, Tix, Tsc | N-FET | S, 125V, Idss>1.5mA, Up<15V | 2b | TO-5 | 2N5542...43 |
| 2 N 4888 | Fch, Spe | Si-P | Vid, 150/150V, 0.05A, 0.3W, >30MHz, hFE=40...400 | 8a | TO-105 | BF 398, BF 423, BF 435...437, 2SC1370, ++ |
| 2 N 4889 | | Si-P | =2N4888: >40MHz, hFE=80...300 | 8a | TO-105 | BF 398, BF 423, BF 435...437, 2SC1370, ++ |
| 2 N 4890(Si) | USA, Mot | Si-P | LFS, 60/40V, 0.5A, 1W, 280MHz, 35/130ns | 2a | TO-5 | BC 161, BC 303...304, 2N2904...05(A), ++ |
| 2 N 4891(L) | Mot, Tix | UJT-P | 30V, 50mA, iEM=1A, 0.3W, Ip<5µA, Iv>2mA, η=0.55...0.82, Rbb=4...9.1kΩ (2N4891...94L) | 7b | SOT-30 | 2N4870 |
| 2 N 4892(L) | | UJT-P | =2N4891: Ip<2µA, Iv>4mA, η=0.51...0.69 | 7b | SOT-30 | 2N4852 |
| 2 N 4893(L) | | UJT-P | =2N4891: Ip<2µA, Iv>2mA, η=0.55...0.82, Rbb=4...12kΩ | 7b | SOT-30 | 2N4851, 2N4947, 2N4948 |
| 2 N 4894(L) | | UJT-P | =2N4891: Ip<1µA, Iv>2mA, η=0.74...0.86, Rbb=4...12kΩ | 7b | SOT-30 | 2N4949 |
| 2 N 4895 | USA, Sgs | Si-N | S, 120/60V, 5A, 1W, >50MHz, hFE=40...120 | 2a | TO-39 | BFT 34, BUX 34, BUY 80 |
| 2 N 4896 | | Si-N | =2N4895: >80MHz, B=100...300 | 2a | TO-39 | BFT 34, BUX 34, BUY 80 |
| 2 N 4897 | | Si-N | =2N4895: 150/80V | 2a | TO-39 | BUY 80 |
| 2 N 4898 | USA, Fch, Mot Rca, Sgs, Tix | Si-P | LFS P, 40/40V, 1/4A, 25W, >3MHz, sat<0.6V(1A) hFE=20...100 (2N4910) | 22a | TO-66 | BD 240, BD 242, BDX 14, 2N3740...41, ++ |
| 2 N 4899 | | Si-P | =2N4898: 60/60V (2N4911) | 22a | TO-66 | BD 240A, BD 242A, BDX 14, 2N3740...41, ++ |
| 2 N 4900 | | Si-P | =2N4898: 80/80V (2N4912) | 22a | TO-66 | BD 240B, BD 242B, BDX 14, 2N3741, ++ |
| 2 N 4901 | USA, Fch, Mot Tho, Tix | Si-P | LFS P, 40/40V, 5/15A, 87.5W, >4MHz, sat<1.5V(5A) hFE=20...80 (2N5067) | 23a | TO-3 | BD 246, BDV 92, BDX 92, 2N5871...72, ++ |
| 2 N 4902 | | Si-P | =2N4901: 60/60V (2N5068) | 23a | TO-3 | BD 246A, BDV 92, BDX 92, 2N5871...72, ++ |
| 2 N 4903 | | Si-P | =2N4901: 80/80V (2N5069) | 23a | TO-3 | BD 246B, BDV 94, BDX 94, 2N5872, ++ |
| 2 N 4904 | | Si-P | =2N4901: hFE=25...100 (2N4913) | 23a | TO-3 | BD 246, BDV 92, BDX 92, 2N5871...72, ++ |
| 2 N 4905 | | Si-P | =2N4901: 60/60V, hFE=25...100 (2N4914) | 23a | TO-3 | BD 246A, BDV 92, BDX 92, 2N5871...72, ++ |
| 2 N 4906 | | Si-P | =2N4901: 80/80V, hFE=25...100 (2N4915) | 23a | TO-3 | BD 246B, BDV 94, BDX 94, 2N5872, ++ |
| 2 N 4907 | USA, Sgs | Si-P | LFS P, 40/40V, -10A, 150W, 4MHz, sat<2V(10A) | 23a | TO-3 | BD 312, BD 546, BDW 22, 2N5875...76, ++ |
| 2 N 4908 | | Si-P | =2N4907: 60/60V | 23a | TO-3 | BD 312, BD 546A, BDW 22A, 2N5875...76, ++ |
| 2 N 4909 | | Si-P | =2N4907: 80/80V | 23a | TO-3 | BD 314, BD 546B, BDW 22B, 2N5876, ++ |
| 2 N 4910 | USA, Fch, Mot Tho, Tix | Si-N | LFS P, 40/40V, 1/4A, 25W, >3MHz, sat<0.6V(1A) hFE=20...100 (2N4898) | 22a | TO-66 | BD 239, BD 241, BDY 78, 2N4231...33, ++ |
| 2 N 4911 | | Si-N | =2N4910: 60/60V (2N4899) | 22a | TO-66 | BD 239A, BD 241A, BDY 78, 2N4232...33, ++ |
| 2 N 4912 | | Si-N | =2N4910: 80/80V (2N4900) | 22a | TO-66 | BD 239B, BD 241B, BDY 78, 2N4233, ++ |
| 2 N 4913 | USA, Fch, Mot Rca, Tx | Si-N | LFS P, 40/40V, 5/15A, 87.5W, >4MHz, sat<1.5V(5A) hFE=25...100 (2N4904) | 22a | TO-66 | BD 245, BDV 91, BDX 91, 2N5873...74, ++ |
| 2 N 4914 | | Si-N | =2N4913: 60/60V (2N4905) | 22a | TO-66 | BD 245A, BDV 91, BDX 91, 2N5873...74, ++ |