

2514096 CRIMSON SEMICONDUCTOR INC

99D 00355 D T-11-11

ZENER DIODES

Zener Type No.	Zener Voltage at $I_{zr}$		Max. Zener Impedance @ $I_{zr}$ Ohms	Zener Voltage Tolerance	Power Rating	Device Package
	Volts	@ mA				
1N5221	2.4	20.0	30.0	No Suffix = 20% Suffix A = 10% Suffix B = 5%	500mw	DO-7
1N5222	2.5	"	"		"	"
1N5223	2.7	"	"		"	"
1N5224	2.8	"	"	"	"	"
1N5225	3.0	"	29.0	"	"	"
1N5226	3.3	"	28.0	"	"	"
1N5227	3.6	"	24.0	"	"	"
1N5228	3.9	"	23.0	"	"	"
1N5229	4.3	"	22.0	"	"	"
1N5230	4.7	"	19.0	"	"	"
1N5231	5.1	"	17.0	"	"	"
1N5232	5.6	"	11.0	"	"	"
1N5233	6.0	"	7.0	"	"	"
1N5234	6.2	"	"	"	"	"
1N5235	6.8	"	5.0	"	"	"
1N5236	7.5	"	6.0	"	"	"
1N5237	8.2	"	8.0	"	"	"
1N5238	8.7	"	"	"	"	"
1N5239	9.1	"	10.0	"	"	"
1N5240	10.0	"	17.0	"	"	"
1N5241	11.0	"	22.0	"	"	"
1N5242	12.0	"	30.0	"	"	"
1N5243	13.0	9.5	13.0	"	"	"
1N5244	14.0	9.0	15.0	"	"	"
1N5245	15.0	8.5	16.0	"	"	"
1N5246	16.0	7.8	17.0	"	"	"
1N5247	17.0	7.4	19.0	"	"	"
1N5248	18.0	7.0	21.0	"	"	"
1N5249	19.0	6.6	23.0	"	"	"
1N5250	20.0	6.2	25.0	"	"	"
1N5251	22.0	5.6	29.0	"	"	"
1N5252	24.0	5.2	33.0	"	"	"
1N5253	25.0	5.0	35.0	"	"	"
1N5254	27.0	4.6	41.0	"	"	"
1N5255	28.0	4.5	44.0	"	"	"
1N5256	30.0	4.2	49.0	"	"	"
1N5257	33.0	3.8	58.0	"	"	"
1N5258	36.0	3.4	70.0	"	"	"
1N5259	39.0	3.2	80.0	"	"	"
1N5260	43.0	3.0	93.0	"	"	"
1N5261	47.0	2.7	105.0	"	"	"
1N5262	51.0	2.5	125.0	"	"	"
1N5263	56.0	2.2	150.0	"	"	"
1N5264	60.0	2.1	170.0	"	"	"
1N5265	62.0	2.0	185.0	"	"	"
1N5266	68.0	1.8	230.0	"	"	"
1N5267	75.0	1.7	270.0	"	"	"
1N5268	82.0	1.5	330.0	"	"	"
1N5269	87.0	1.4	370.0	"	"	"
1N5270	91.0	"	400.0	"	"	"
1N5271	100.0	1.3	500.0	"	"	"
1N5272	110.0	1.1	750.0	"	"	"