

2 SB 1196	Si-P	NF-L, 70V, 4A, 25W	15c	(BD 244 C)	17j	3
2 SB 1199	Si-P	NF, 15V, 1A, 0,3W	9c	BC 327	7a	
2 SB 1201	Si-P	S-L, lo-sat, 60V, 2A, 15W, 150MHz	30j	-	-	
2 SB 1202	Si-P	S-L, lo-sat, 60V, 3A, 15W, 150MHz	30j	-	-	
2 SB 1203	Si-P	S-L, lo-sat, 60V, 5A, 20W, 130MHz	30j	-	-	
2 SB 1204	Si-P	S-L, lo-sat, 60V, 8A, 20W, 130MHz	30j	-	-	
2 SB 1205	Si-P	S-L, lo-sat, 25V, 5A, 10W, 320MHz	30j	-	-	
2 SB 1206	Si-P	=2SB774: 0,3W	40c	->2SB774	-	
2 SB 1207	Si-P	Uni, 15V, 0,5A, 0,3W, 130MHz	40c	BC 327	7a	
2 SB 1209	Si-P	NF/S, 400/400V, 0,1A, 1W, 70MHz	9c	-	-	
2 SB 1210	Si-P	NF, 20V, 2A, 0,5W, 80MHz	7c	2SB892	7c(9mm)	
2 SB 1212	Si-P	NF, 160V, 1,5A, 0,9W, 50MHz	7c(9mm)	2SB1212	7c(9mm)	
2 SB 1213	Si-P-Darl+Di	NF/S-L, 120V, 10A, 30W, B=5000	15c	-	-	
2 SB 1214	Si-P-Darl+Di	NF/S-L, 80V, 3A, 15W, B=5000	30j	-	-	
2 SB 1215	Si-P	S-L, lo-sat, 120V, 3A, 20W, 130MHz	30j	-	-	
2 SB 1216	Si-P	S-L, lo-sat, 120V, 4A, 20W, 130MHz	30j	-	-	
2 SB 1217	Si-P	NF/S-L, lo-sat, 60V, 3A, 10W, 50MHz	14h	2SB986	14h	
2 SB 1218	Si-P	=2SB709:	35a(2mm)	-	-	
2 SB 1218 A	Si-P	=2SB709A:	35a(2mm)	-	-	
2 SB 1219	Si-P	=2SB710:	35a(2mm)	-	-	
2 SB 1219 A	Si-P	=2SB710A:	35a(2mm)	-	-	
2 SB 1221	Si-P	Vid, 250/200V, 0,07A, 1W, 80MHz	7c(9mm)	BF 421A	7c	
2 SB 1223	Si-P-Darl+Di	NF/S-L, 70V, 4A, 20W, 20MHz, B=5000	17c	-	-	
2 SB 1224	Si-P-Darl+Di	NF/S-L, 70V, 7A, 25W, 20MHz, B=5000	17c	2SB1020	17c	
2 SB 1225	Si-P-Darl+Di	NF/S-L, 70V, 10A, 30W, 20MHz, B=5000	17c	-	-	
2 SB 1226	Si-P-Darl+Di	NF/S-L, 110V, 3A, 20W, 20MHz, B=4000	17c	-	-	
2 SB 1227	Si-P-Darl+Di	NF/S-L, 110V, 5A, 25W, 20MHz, B=4000	17c	-	-	
2 SB 1228	Si-P-Darl+Di	NF/S-L, 110V, 8A, 30W, 20MHz, B=4000	17c	-	-	
2 SB 1229	Si-P	S, lo-sat, 60V, 2A, 0,75W, 150MHz	7c	2SB892	7c	
2 SB 1230	Si-P	NF/S-L, lo-sat, 110V, 15A, 100W	18j	-	-	
2 SB 1231	Si-P	NF/S-L, lo-sat, 110V, 25A, 120W	18j	-	-	
2 SB 1232	Si-P	NF/S-L, lo-sat, 110V, 40A, 150W	18j	-	-	
2 SB 1233(A)	Si-P	=2SB1192(A): 15W	=30j	(2SB861)	17j	6
2 SB 1234	Si-P-Darl	=2SB1235: SMD	35a	-	-	
2 SB 1235	Si-P-Darl	NF, 80V, 0,2A, B>5000	40c	-	-	
2 SB 1236	Si-P	=2SB1130,A(M,AM): Pins = 14mm	9c	->2SB1130...	-	
2 SB 1237	Si-P	=2SB909: Pins = 14mm	9c	->2SB909	-	
2 SB 1238	Si-P	=2SB910: Pins = 14mm	9c	->2SB910	-	
2 SB 1239	Si-P-Darl	=2SB1076(M): Pins = 14mm	9c	-	-	
2 SB 1240	Si-P	=2SB911: Pins = 14mm	9c	->2SB911	-	
2 SB 1241	Si-P	Uni, 80V, 1A, 1W, 100MHz	9c	BC 640	7c	
2 SB 1242	Si-P	Uni, 50V, 1A, 1W	9c	BC 640	7c	
2 SB 1243	Si-P	=2SB1184:	9c	->2SB1066M	-	
2 SB 1244	Si-P	Vid, 160/160V, 0,1A, 0,9W, 140MHz	7c(9mm)	BF 421 A	7c	
2 SB 1245	Si-P	=2SB1244: 200/200V	7c(9mm)	BF 421 A	7c	
2 SB 1246	Si-P	NF/S-L, 40V, 2A, 10W	30j	2SA1593	30j	
2 SB 1247	Si-P	NF/S-L, 60V, 1,5A, 10W	30j	2SA1593	30j	
2 SB 1248	Si-P	NF/S-L, 110V, 0,8A, 10W	30j	2SA1593	30j	
2 SB 1249	Si-P	NF/S-L, 130V, 0,8A, 10W	30j	-	-	
2 SB 1250	Si-P-Darl	NF/S-L, 100V, 3A, 35W, 20MHz, B>5000	17c	(2SB1020)	17c	13
2 SB 1251	Si-P-Darl	NF/S-L, 110V, 4A, 40W, 20MHz, B>5000	17c	(2SB1020)	17c	13
2 SB 1252	Si-P-Darl	NF/S-L, 120V, 5A, 45W, 20MHz, B>5000	17c	-	-	
2 SB 1253	Si-P-Darl	NF/S-L, 130V, 6A, 50W, 20MHz, B>5000	16c	-	-	
2 SB 1254	Si-P-Darl	NF/S-L, 160V, 7A, 70W, 20MHz, B>5000	16c	-	-	
2 SB 1255	Si-P-Darl	NF/S-L, 160V, 8A, 100W, 20MHz, B>5000	16c	-	-	
2 SB 1256	Si-P-Darl+Di	NF/S, 100V, 2A, 1,2W, B=2000	7c(9mm)	-	-	