

LM 2808(N)	Nsc	LIN-IC	TV, Ton/Sound System, NF-E, 2,6W(16V/8Ω)	18-DIP	-	-	-	-
LM 2877(P)	Nsc	LIN-IC	Dual LF Out, 6...24V, 2x 4,5W(20V/8Ω)	11-SIL	-	-	-	-
LM 2878(P)	Nsc	LIN-IC	Dual LF Out, 6...32V, 2x 5,5W(22V/8Ω)	11-SIL	-	-	-	-
LM 2879(T)	Nsc	LIN-IC	Dual LF Out, 6...32V, 2x 8W(28V/8Ω)	11-SQL	-	-	-	-
LM 2889(N)	Nsc	LIN-IC	TV, Video Modulator, Ucc=10...16V	18-DIP	-	-	-	-
LM 2893(N)	Nsc	LIN-IC	Bi-Line Carrier-Current Transceiver, 50...300kHz	18-DIP	-	-	-	-
LM 2895(P)	Nsc	LIN-IC	LF Out, 3...15V, 4,3W(12V/4Ω)	11-SIL	-	-	-	-
LM 2896(P-1,P-2)	Nsc	LIN-IC	=LM 2895: Dual, 2x2,5W(P-1)/1x9W(P-2)(12V/8Ω)	11-SIL	-	-	-	-
LM 2900 D,J,N	Mot,Nsc,Tix	OP-IC	Quad, ±16V, 50mA, -40...+85°	14-DIC,DIP	-	-	-	NJM 2900... (LM 3900...) ¹⁶
LM 2901 O,FP,M	Nsc,Tho	KOP-IC	=LM 2901DP,N: SMD	14-MDIP	-	-	-	... 139... 239... 2901...
LM 2901(A)DP,F,J,N	Mot,Nsc,++	KOP-IC	Quad, Serie 139, ±18V, -40...+85°	14-DIP,DIC	(LM 339 N) ¹⁶	14-DIP	-	... 139... 239... 2901...
LM 2901 GC	Tho	KOP-IC	=LM 2901(A)DP,J,N: SMD, -40...+105°	20-LCC	-	-	-	... 139... 239... 2901...
LM 2901 W	Tix	KOP-IC	=LM 2901(A)DP,J,N: Min	14-FLP	-	-	-	... 139... 239... 2901...
LM 2902 CM,D,FP,M	Nsc,Tho,Tix	OP-IC	=LM 124(A)DP,N: SMD, ±13V, -40...+85°	14-MDIP	-	-	-	... 124... 224... 2902...
LM 2902 DP,J,N	Mot,Nsc,++	OP-IC	=LM 124(A)DP,N: 26V, -40...+85°	14-DIP,DIC	(LM 324 N) ¹⁶	14-DIP	-	... 124... 224... 2902...
LM 2903 CM,D,FP,M	Nsc,Tho,Tix	KOP-IC	=LM 193(A)H: SMD, -40...+85°	8-MDIP	-	-	-	... 193... 293... 2903...
LM 2903DP,J,G,N,P	Mot,Nsc,++	KOP-IC	=LM 193(A)H: -40...+85°	8-DIP,DIC	(LM 393/8D) ¹⁶	8-DIP	-	... 193... 293... 2903...
LM 2903 H,L	Phi,Tix	KOP-IC	=LM 193(A)H: -40...+85°	TO-99	-	-	-	... 193... 293... 2903...
LM 2903 U	Tix	KOP-IC	=LM 193(A)H: -40...+85°	10-FLP	-	-	-	... 193... 293... 2903...
LM 2904 CM,D,FP,M	Nsc,Tho,Tix	OP-IC	=LM 158(A)H: SMD, ±13V, -40...+85°	8-MDIP	-	-	-	... 158... 258... 1558... 2904...
LM 2904DP,G,J,N,P	Mot,Nsc,++	OP-IC	=LM 158(A)H: ±13V, -40...+85°	8-DIP,DIC	4558/8-D	8-DIP	-	... 158... 258... 1558... 2904...
LM 2904 H,L	Nsc,Mot,Tix	OP-IC	=LM 158(A)H: -40...+85°	TO-99	-	-	-	... 158... 258... 1558... 2904...
LM 2904 U	Tix	OP-IC	=LM 158(A)H: ±13V, -40...+85°	10-FLP	-	-	-	... 158... 258... 1558... 2904...
LM 2905(N)	Nsc	LIN-IC	=LM 122(H): -40...+85°	8-DIP	-	-	-	-
LM 2907 N	Nsc,Tix	LIN-IC	F/V-Converter, Ucc<28V, -40...+85°	14-DIP	-	-	-	-
LM 2907 N-8,P	Nsc,Tix	LIN-IC	=LM 2907N: Fig. >	8-DIP	-	-	-	-
LM 2917 N	Nsc,Tix	LIN-IC	F/V-Converter, Ucc<28V, -40...+85°	14-DIP	-	-	-	-
LM 2917 N-8	Nsc,Tix	LIN-IC	=LM 2917N: Fig. >	8-DIP	-	-	-	-
LM 2924 N	Nsc	OP/KOP-IC	=LM 192H: ±13V, -40...+85°	8-DIP	-	-	-	LM 192... LM 292...
LM 2930 LP-...	Tix	Z-IC	=LM 2930T-...	7b	TO-92	-	-	NJM 2930L-xx
LM 2930(A)KC,T-5.0	Nsc,Sgs,Tix	Z-IC	lo-drop, +5V, 0,4>0,15A, A=verbess./improved Vers.	17b	TO-220	-	-	NJM 2930-05
LM 2930 KC,T-8.0	Nsc,Tix	Z-IC	lo-drop, +8V, 0,4>0,15A	17b	TO-220	-	-	NJM 2930-08
LM 2931(A)D-5.0	Mot	Z-IC	=LM 2930T-... SMD	8-MDIP	-	-	-	-
LM 2931(A)T-5.0	Mot,Nsc,Sgs	Z-IC	lo-drop, +5V, 0,4>0,15A, A=verbess./improved Vers.	17b	TO-220	-	-	-
LM 2931(A)Z,LP-5.0	Mot,Nsc,Tix	Z-IC	=LM 2930T-...	7b	TO-92	-	-	-
LM 2931 T	Mot,Nsc	Z-IC	=LM 2930T-... 3...24V	17/5Pin	TO-220/5	-	-	-
LM 2935	Sgs	Z-IC	Dual, lo-drop, 5V/0,75, 5V/0,01A	17/5Pin	TO-220/5	-	-	-
LM 2936 M-5.0	Nsc	Z-IC	=LM 2936Z-...	8-MDIP	-	-	-	-
LM 2936 Z-5.0	Nsc	Z-IC	+5V, 0,05A	7b	TO-92	78L05/TO-92	7b	... 78L05 (TO-92)
LM 2940(C)T-12	Nsc	Z-IC	+5V, 1A, lo-drop	17b	TO-220	-	-	-
LM 3009	Nsc	IC	-	-	-	-	-	-
LM 3011(H)	Nsc	LIN-IC	Breitb. Vst./Wideband Amp., Ucc<15V	TO-100	-	-	-	CA 3011
LM 3045 J,N	Nsc,Sgs	LIN-IC	5x NPN Trans. Array, 20/15V, 0,05A, -55...+125°	14-DIP,DIC	-	-	-	CA 3045, TBA 331, µA 3045
LM 3046 J,N	Nsc,Sgs	LIN-IC	=LM 3045: -40...+85°	14-DIP,DIC	-	-	-	CA 3046, TBA 331, µA 3046
LM 3046 D,M	Nsc,Sgs	LIN-IC	=LM 3046J,N: SMD	14-MDIP	-	-	-	-
LM 3064(N,N-01)	Nsc	LIN-IC	TV, AFT, AGC, Ucc=30V	14-DIP	-	-	-	-
LM 3065(N)	Nsc	LIN-IC	TV, Sound IF, FM IF	14-DIP	-	-	-	AN 241, CA 3065, HA 1125, KA 2101, LA 1365, MC 1358, TA 7176, ULN 2165 CA 3075
LM 3075(N,N-01)	Nsc	LIN-IC	FM Detector/Limiter, LF Preamp., Ucc<12,5V	14-DIP	-	-	-	CA 3086, TBA 331, µA 3086
LM 3080(A)J,N	Nsc	OP-IC	OTA, ±18(A=±22)V, 0...+70(A=-55...+125)°	8-DIC,DIP	-	-	-	CA 3089, TCA 3089, TDA 1200(A)
LM 3086(N)	Nsc	LIN-IC	5x NPN Trans. Array, 20/15V, 0,05A, -40...+85°	14-DIP	-	-	-	-
LM 3089(N)	Nsc	LIN-IC	TV, Sound IF, FM IF, AGC, AFC, Ucc=12V	16-DIP	-	-	-	CA 3189E, TCA 3189
LM 3146 M	Nsc	LIN-IC	=LM 3146(N): SMD	14-MDIP	-	-	-	-
LM 3146(N)	Nsc	LIN-IC	5x NPN Trans. Array, 40/30V, 0,05A, -40...+85°	14-DIP	-	-	-	-
LM 3189 N	Nsc	LIN-IC	FM IF, Dem, LF Inp, AFC, AGC(prog.), Ucc=8,5...16V	16-DIP	-	-	-	-
LM 3211	Say	PMOS-IC	6 Bit Frequenzteiler/Prescaler f. El. Orgel/Organ	-	-	-	-	-
LM 3216	Say	PMOS-IC	8 Bit Frequenzteiler/Prescaler f. El. Orgel/Organ	14-DIP	-	-	-	-
LM 3301 N	Nsc	OP-IC	=LM 2900...: ±14V	14-DIP	-	-	-	LM 2900...
LM 3302 DP,J,L,N,P	Mot,Nsc,++	KOP-IC	Quad, Serie 139, ±14V, -40...+85°	14-DIP,DIC	(LM 339 N) ¹⁶	14-DIP	-	... 139... 239... 2901... 3302...
LM 3361(A)N	Nsc	LIN-IC	FM IF, Schmalb./Narrow Band, Ucc=2...9V, A=improved	16-DIP	-	-	-	KA 3361, MC 3361
LM 3401 N	Nsc	OP-IC	=LM 2900...: ±9V, 0...+75°	14-DIP	-	-	-	LM 2900... LM 3301... LM 3900...
LM 3524	Nsc	LIN-IC	=SG 3524	16-DIP	-	-	-	=SG 3524
LM 3524 J,N	Nsc	LIN-IC	=LM 1524: 0...+70°	16-DIC,DIP	-	-	-	=SG 3524...
LM 3700	Say	ROM-IC	4096x10Bit	28-DIP	-	-	-	-
LM 3710	Say	ROM-IC	8192x10Bit	28-DIP	-	-	-	-
LM 3764	Say	EPROM-IC	NMOS, 8192 x 8 Bit, <250...450ns, 2764 Pincomp.	28-DIP	-	-	-	-
LM 3820(N)	Nsc	LIN-IC	AM Radio System, Ucc=6V	14-DIP	-	-	-	-
LM 3900 D,M	Mot,Nsc,Tix	OP-IC	=LM 2900...: SMD, 0...+70°	14-MDIP	-	-	-	NJM 2900... NJM 3900...
LM 3900 J,N	Mot,Nsc	OP-IC	=LM 2900...: 0...+70°	14-DIC,DIP	-	-	-	LM 2900...
LM 3905(N)	Nsc	LIN-IC	=LM 122(H): 0...+70°	8-DIP	-	-	-	-
LM 3909(N)	Nsc	LIN-IC	LED Flasher/Oscillator, Ucc=1...5V	8-DIP	-	-	-	-
LM 3911(N)	Nsc	LIN-IC	Temp. Sensor/Controller, Volt. Ref., OP-Amp.	8-DIP	-	-	-	-
LM 3914 J,N	Nsc	LIN-IC	10 LED Pegelanzeige/Level Meter Driver, Iq=2...30mA	18-DIC,DIP	-	-	-	-
LM 3914 V	Nsc	LIN-IC	=LM 3914(N):	20-PLCC	-	-	-	-
LM 3915 J,N	Nsc	LIN-IC	10 LED Pegelanzeige/Level Meter Driver, Iq=1...30mA	18-DIC,DIP	-	-	-	-
LM 3916 J,N	Nsc	LIN-IC	10 LED Pegelanzeige/Level Meter Driver, Iq=1...30mA	18-DIC,DIP	-	-	-	-
LM 3999 Z	Nsc	Ref-Z-IC	5,95V, ±5%, 0,6<2,2Ω, <0,0005%/°C, 0...+70°	7(AK+)	TO-92	-	-	-
LM 4250(C)H	Nsc	OP-IC	lo-power, progr., ±18V, -55...+125° (C=0...+70°)	TO-99	-	-	-	... 1250... 3250... 4250...
LM 4250(C)J,N	Nsc	OP-IC	=LM 4250(C): Fig. >	8-DIC,DIP	-	-	-	... 1250... 3250... 4250...
LM 4250(C)M	Nsc	OP-IC	=LM 4250(C): SMD	8-MDIP	-	-	-	... 1250... 3250... 4050...
LM 4500 A	Nsc	LIN-IC	PLL Stereo-Decoder, Blend, o. Spulen/wo. Inductors	16-DIP	TCA 4500 A	16-DIP	-	TCA 4500A, UL 1261N
LM 6402(A,H,L)	Say	µC-IC	4 Bit, 2KB ROM, 128x4Bit RAM	42-DIP	-	-	-	-
LM 6405(A,H,L)	Say	µC-IC	4 Bit, 1kB ROM, 64x4Bit RAM	42-DIP	-	-	-	-
LM 6413 E	Say	µC-IC	4 Bit, 1kB ROM, 64x4Bit RAM	28-DIP	-	-	-	-
LM 6416 E	Say	µC-IC	4 Bit, 1kB ROM, 64x4Bit RAM	28-DIP	-	-	-	-
LM 6417 E	Say	µC-IC	4 Bit	22-DIP	-	-	-	-
LM 6497	Say	µC-IC	Chip	-	-	-	-	-
LM 6499	Say	µC-IC	Chip	-	-	-	-	-
LM 7000(N)	Say	NMOS-IC	AM/FM Tuning PLL Frequ.-Synthesizer	20-DIP	LM 7000(N)	20-DIP	-	-
LM 7001	Say	NMOS-IC	AM/FM Tuning PLL Frequ.-Synthesizer	16-DIP	-	-	-	-
LM 7001 M	Say	NMOS-IC	=LC 7001: SMD	20-MDIP	-	-	-	-
LM 7005	Say	NMOS-IC	AM...UHF Tuning PLL Frequ.-Synthesizer	24-SDIP	-	-	-	-
LM 7006(H)	Say	NMOS-IC	Telecom, PLL Synthesizer f. Cordl.Ph., 200...400MHz	20-DIP	-	-	-	-