

LM 318 H,L	OP-IC	=LM 118H: 0...+70°	TO-99	-	
LM 318 JG,J-8	OP-IC	=LM 118H: 0...+70°	8-DIC	(318/8-D)	8-DIP
LM 320 H-...	Z-IC	=LM 320T-...: 0,5A, 2W	2f	-	
LM 320 K,KC-...	Z-IC	=LM 320T-...: 1,5A, 20W	23d	-	
LM 320 KC-...	Z-IC	=LM 320T-...	17c	79xx/TO-220	17c
LM 320 LZ-...	Z-IC	=LM 320T-...: 0,1A, 1,2W	7a	79Lxx/TO-92	7a
LM 320 MLP-...	Z-IC	=LM 320T-...: 0,25A, 7,5W	13c	(79xx/TO-220)	17c
LM 320 MP-...	Z-IC	=LM 320T-...: 0,5A, 7,5W	13c	(79xx/TO-220)	17c
LM 320 T-5.0	Z-IC	-5V, 1,5A, 15W, 0...+125°	17c	7905/TO-220	17c
LM 320 T-5.2	Z-IC	-5,2V, 1,5A, 15W, 0...+125°	17c	-	
LM 320 T-6.0	Z-IC	-6V, 1,5A, 15W, 0...+125°	17c	-	
LM 320 T-8.0	Z-IC	-8V, 1,5A, 15W, 0...+125°	17c	-	
LM 320 T-9.0	Z-IC	-9V, 1,5A, 15W, 0...+125°	17c	-	
LM 320 T-12	Z-IC	-12V, 1,5A, 15W, 0...+125°	17c	7912/TO-220	17c
LM 320 T-15	Z-IC	-15V, 1,5A, 15W, 0...+125°	17c	7915/TO-220	17c
LM 320 T-18	Z-IC	-18V, 1,5A, 15W, 0...+125°	17c	-	
LM 320 T-24	Z-IC	-24V, 1,5A, 15W, 0...+125°	17c	-	
LM 323 H,SP3	Z-IC	=LM 123(A)K: 0...+125°	18b	-	
LM 323(A)K	Z-IC	=LM 123(A)K: 0...+125°	23a	-	
LM 323(A)T	Z-IC	=LM 123(A)K: 0...+125°	17b	-	
LM 324(A)CM,D,FP,M	OP-IC	=LM 124(A)DP,N: SMD, 0...+70°	14-MDIP	-	
LM 324(A)DG,F,J	OP-IC	=LM 124(A)DP,N: 0...+70°	14-DIC	LM 324 N	14-DIP
LM 324(A)DP,N	OP-IC	=LM 124(A)DP,N: 0...+70°	14-DIP	LM 324 N	14-DIP
LM 337 H	Z-IC	=LM 137H: 0...+125°	2l	-	
LM 337 HV(H,K)	Z-IC	=LM 137H: -1,2...-47V, -0...+125°	-	-	
LM 337 K	Z-IC	=LM 137H: >1,5A, 20W, 0...+125°	23m	-	
LM 337 KC,SP,T	Z-IC	=LM 137H: >1,5A, 15W, 0...+125°	17n	-	
LM 317 LZ	Z-IC	=LM 137H: >0,1A, >0,62W, 0...+125°	7o	-	
LM 337 MP	Z-IC	=LM 137H: >0,5A, 7,5W, 0...+125°	13n	-	
LM 337 MR	Z-IC	=LM 137H: 0...+125	22m	-	
LM 337 MT	Z-IC	=LM 137H: >0,5A, 0...+125°	17n	-	
LM 337 SP3	Z-IC	=LM 137H: >1,5A, 20W, 0...+125°	18n	-	
LM 339(A)CM,D,FP,M	KOP-IC	=LM 139...: SMD, 0...+70°	14-MDIP	-	
LM 339(A)DP,N	KOP-IC	=LM 139...: 0...+70°	14-DIP	LM 339 N	14-DIP
LM 339(A)F,J	KOP-IC	=LM 139...: 0...+70°	14-DIC	LM 339 N	14-DIP
LM 340 DA-5	Z-IC	+5V, 1A, 15W, 0...+70°	23a	7805/TO-3	23a
LM 340 DA-12	Z-IC	+12V, 1A, 15W, 0...+70°	23a	7812/TO-3	23a
LM 340(A)K,KC-5	Z-IC	+5V, 1,5A, 20W, 4%(A=2%), 0...+125°	23a	7805/TO-3	23a
LM 340(A)K,KC-6	Z-IC	+6V, 1,5A, 20W, 4%(A=2%), 0...+125°	23a	-	
LM 340(A)K,KC-8	Z-IC	+8V, 1,5A, 20W, 4%(A=2%), 0...+125°	23a	-	
LM 340(A)K,KC-10	Z-IC	+10V, 1,5A, 20W, 4%(A=2%), 0...+125°	23a	-	
LM 340(A)K,KC-12	Z-IC	+12V, 1,5A, 20W, 4%(A=2%), 0...+125°	23a	7812/TO-3	23a
LM 340(A)K,KC-15	Z-IC	+15V, 1,5A, 20W, 4%(A=2%), 0...+125°	23a	-	
LM 340(A)K,KC-18	Z-IC	+18V, 1,5A, 20W, 4%(A=2%), 0...+125°	23a	-	
LM 340(A)K,KC-24	Z-IC	+24V, 1,5A, 20W, 4%(A=2%), 0...+125°	23a	-	
LM 340(A)KC,T,U-5	Z-IC	+5V, 1,5A, 15W, 4%(A=2%), 0...+125°	17b	7805/TO-220	17b
LM 340(A)KC,T,U-6	Z-IC	+6V, 1,5A, 15W, 4%(A=2%), 0...+125°	17b	7806/TO-220	17b
LM 340(A)KC,T,U-8	Z-IC	+8V, 1,5A, 15W, 4%(A=2%), 0...+125°	17b	7808/TO-220	17b
LM 340(A)KC,T,U-10	Z-IC	+10V, 1,5A, 15W, 4%(A=2%), 0...+125°	17b	7810/TO-220	17b
LM 340(A)KC,T,U-12	Z-IC	+12V, 1,5A, 15W, 4%(A=2%), 0...+125°	17b	7812/TO-220	17b
LM 340(A)KC,T,U-15	Z-IC	+15V, 1,5A, 15W, 4%(A=2%), 0...+125°	17b	7815/TO-220	17b
LM 340(A)KC,T,U-18	Z-IC	+18V, 1,5A, 15W, 4%(A=2%)	17b	7818/TO-220	17b
LM 340(A)KC,T,U-24	Z-IC	+24V, 1,5A, 15W, 4%(A=2%), 0...+125°	17b	7824/TO-220	17b
LM 340 LAH-...	Z-IC	=LM 340(A)K,KC-...: 0,1A, 2W	2e	-	
LM 340 LAZ-...	Z-IC	=LM 340(A)K-...: 0,1A, 1,2W	7b	78Lxx/TO-92	7b
LM 341 P-5	Z-IC	+5V, 0,5A, 7,5W, 0...+70°	13b	(7805/TO-220)	17b