

2 SC 1277	Si-N	Uni, 60V, 0,5A, 0,25W, 60MHz	7c	BC 639	7c
2 SC 1278	Si-N	Nix, 150V, 0,05A, 0,25W, 150MHz	7c	BF 420 A	7c
2 SC 1279(S)	Si-N	=2SC1278: 180V	7c	BF 420 A	7c
2 SC 1280(S)	Si-N-Darl	Uni, 15V, 0,3A, 0,25W, B>5000	7c	2SD1153	7c(9mm)
2 SC 1280 A(AS)	Si-N-Darl	=2SC1280: 40V, B>12000	7c	BC 879	7c
2 SC 1281	Si-N	Uni, 20V, 0,02A, 0,3W, 120MHz	2a	BC 546	7a
2 SC 1282	Si-N	=2SC1282: 70V	2a	BC 546	7a
2 SC 1283	Si-N	=2SC1281: 110V	2a	2SC2632	7c(9mm)
2 SC 1284	Si-N	UHF, 30V, 0,05A, 700MHz	7c	2SC2570 A	7f
2 SC 1285	Si-N	Uni, 40V, 0,1A, 0,2W, 140MHz	7c	BC 546	7a
2 SC 1286	Si-N	TV-ZF, 25V, 0,05A, 400MHz	7c	BF 198, BF 199	7d
2 SC 1292	Si-N	S-L, 300/300V, 2,5A, 80W	23a	BU 426 A	18j
2 SC 1293	Si-N	HF, 25V, 0,05A, 400MHz	7c	BF 189, BF 199	7d
2 SC 1295	Si-N	TV-HA, 1000/350V, 2A, 40W	23a	2SC1413	23a
2 SC 1296	Si-N	TV-HA, 1300/400V, 5A, 50W	23a	BU 208 A	23a
2 SC 1303(Z)	Si-N	VHF-Tr/E, 40V, 0,3A, PQ=0,6W(175MHz)	2a	-	-
2 SC 1304	Si-N	NF-L, 300/300V, 0,5A, 20W, 7MHz	22a	(BUX 85)	17j
2 SC 1306	Si-N	HF-L, 65V, 3A(ss), PQ=5,5W(50MHz)	17j	-	-
2 SC 1307	Si-N	HF-L, 70V, 8A(ss), PQ=15W(50MHz)	17j	-	-
2 SC 1308	Si-N	TV-HA, 1500/400V, 7A, 50W	23a	BU 2508 A	18j
2 SC 1309	Si-N	TV-VA, 1200/500V, 5A, 80W	23a	2SC1413	23a
2 SC 1310	Si-N	Uni, ra, 50V, 0,2A, 0,3W, 200MHz	41c	BC 550	7a
2 SC 1311	Si-N	=2SC1310: AM/FM	41c	BF 255	7d
2 SC 1312	Si-N	Uni, ra, 35V, 0,1A, 0,2W, 150MHz	7b	BC 550	7a
2 SC 1313	Si-N	=2SC1312: 50V	7b	BC 550	7a
2 SC 1316	Si-N	S-L, 750/750V, 2A, 23W, 8,5MHz	22a	-	-
2 SC 1317	Si-N	Uni, 30V, 0,5A, 0,625W, 200MHz	7c	BC 639	7c
2 SC 1318	Si-N	=2SC1317: 60V	7c	BC 639	7c
2 SC 1318 A	Si-N	=2SC1351: 80V	7c	BC 639	7c
2 SC 1319	Si-N	HF/ZF, re, 40V, 25mA, 600MHz	7c	BF 198	7d
2 SC 1320	Si-N	HF/ZF, 50V, 30mA, 850MHz	7c	BF 199	7d
2 SC 1321	Si-N	SMD, UHF, 30V, 10mA, 900MHz	35a	-	-
2 SC 1322	Si-N	S-L, 250/200V, 15A, 100W, 27MHz	23a	2SC3263	18j
2 SC 1325(A)	Si-N	CTV-HA, 1500/600V, 6A, 80W	23a	BU 208A	23a
2 SC 1327	Si-N	Uni, ra, 35V, 0,05A, 0,15W, 250MHz	7c	BC 550	7a
2 SC 1328	Si-N	=2SC1327: 55V	7c	BC 550	7a
2 SC 1330	Si-N	Uni, 50V, 0,1A, 0,4W, 250MHz	7c°	BC 546	7a
2 SC 1331	Si-N	ZF, UHF, 20V, 0,02A, 750MHz	5g	2SC2570 A	7f
2 SC 1335	Si-N	Uni, ra, 30V, 0,1A, 0,2W, 230MHz	9b	BC 550	7a
2 SC 1342	Si-N	FM-V/M/O, 320MHz	9b, 7c	BF 255	7d
2 SC 1343(H)	Si-N	NF/S-L, 150V, 10A, 100W, 14MHz	23a	2SC3263	18j
2 SC 1344	Si-N	NF, ra, 30V, 0,1A, 0,2W, 230MHz	9b, 7c	BC 550	7a
2 SC 1345(K)	Si-N	=2SC1344: 55V	9b, 7c	BC 550	7a
2 SC 1346	Si-N	=2SC1317: 0,6W	7c°	BC 639	7c
2 SC 1347	Si-N	=2SC1318: 0,6W	7c°	BC 639	7c
2 SC 1348(-1.....3)	Si-N	TV-HA, 1000...1200V, 4A, 125W, 5MHz	23a	(BU 2508 A)	18j
2 SC 1358(A)	Si-N	TV-HA (90°), 1400/500V, 4,5A, 50W	23a	BU 208 A	23a
2 SC 1359	Si-N	Uni, 30V, 0,03A, 0,4W, 250MHz	7c	BC 546, BF 255	7a, 7d
2 SC 1360(A)	Si-N	TV-ZF, 50(A=60)V, 0,05A, 1W, >300MHz	7c(9mm)	BF 959	7d
2 SC 1361	Si-N	Uni, ra, 25V, 0,2A, 0,25W, 140MHz	7c	BC 550	7a
2 SC 1362	Si-N	=2SC1361: 50V	7c	BC 550	7a
2 SC 1363	Si-N	Uni, 25V, 0,2A, 0,25W, 140MHz	7c	BC 546	7a
2 SC 1364	Si-N	=2SC1363: 50V	7c	BC 546	7a
2 SC 1367(A)	Si-N	TV-VA, 1000V, 1A, 50W, 6MHz	23a	(2SC1413)	23a
2 SC 1368	Si-N	NF/S-L, 25V, 1,5A, 8W, 180MHz	14h	BD 139	14h
2 SC 1372	Si-N	Uni, 30V, 0,2A, 0,2W, 250MHz	7c	BC 546	7a

P.F. Supp

\*

\*

\*