

2 SC 2589	Si-N	NF/S-L, 180/180V, 10A, 200W, 60MHz	23a	MJ 15015	23a	
2 SC 2590	Si-N	NF/S-L, 120/120V, 0,5A, 5W, 200MHz	14h	2SC3116	14h	*
2 SC 2591	Si-N	NF/S-L, 150/150V, 1A, 20W, 200MHz	17j	2SC2344	17j	
2 SC 2592	Si-N	=2SC2591: 180/180V	17j	2SC2344	17j	
2 SC 2594	Si-N	NF/S-L, 40V, 5A, 10W, 150MHz	14h	2SC3420	14b	
2 SC 2602	Si-N	Uni, ra, MC-Cartridge, 70V, 0,2A, 0,5W	7b	2SC2632	7c(9mm)	
2 SC 2603	Si-N	Uni, 50V, 0,2A, 0,3W, 200MHz	41c	BC 546	7a	
2 SC 2604	Si-N	Uni, ra, 30V, 0,1A, 0,2W, 230MHz	7c	BC 550	7a	
2 SC 2605	Si-N	=2SC2604: 50V	7c	BC 550	7a	
2 SC 2606	Si-N	Vid-L, 300/300V, 0,05A, 30MHz	=17j	2SC1505	17j	
2 SC 2607	Si-N	S-L, 200/200V, 15A, 150W, 20MHz	23a	MJ 15015	23a	
2 SC 2608	Si-N	=2SC2607: 17A, 200W	23a	(2SC3264)	20j	4
2 SC 2610	Si-N	Vid, 300V, 0,1A, 0,8W, 80MHz	7c(9mm)	2SC3468	7c(9mm)	
2 SC 2611	Si-N	=2SC2610:	14h	BF 459	14h	
2 SC 2612	Si-N	S-L, 500/400V, 3A, 30W	17j	BUT 11 A	17j	
2 SC 2613(K)	Si-N	=2SC2612: 5A, 40W	17j	BUT 11 A	17j	
2 SC 2614	Si-N	=2SC2612: 5A, 60W	20j	-	-	
2 SC 2615	Si-N	=2SC2612: 8A, 80W	20j	-	-	
2 SC 2616	Si-N	=2SC2612: 10A, 100W	23a	S 2530 A	23a	
2 SC 2617	Si-N	=2SC2612: 15A, 125W	23a	-	-	
2 SC 2618	Si-N	SMD, Uni, 35V, 0,5A, 50MHz	35a	BC 817	35a	
2 SC 2619	Si-N	SMD, Uni, 30V, 0,1A, 230MHz	35a	BC 846	35a	
2 SC 2621	Si-N	Vid, 300/300V, 0,2A, 10W, >50MHz	14h	BF 459	14h	
2 SC 2623	Si-N	S-L, 450/400V, 20A, 100W, <1/4µs	23a	-	-	
2 SC 2624	Si-N	S-L, 450/400V, 5A, 80W, <1/3µs	18j	BU 426 A	18j	
2 SC 2625	Si-N	=2SC2624: 10A	18j	BUW 13 A	18j	
2 SC 2626	Si-N	=2SC2624: 400/300V, 15A, <0,8/2,8µs	18j	BUW 13 A	18j	
2 SC 2631	Si-N	Uni, ra, 150V, 0,05A, 0,75W, 160MHz	7c	2SC2632	7c(9mm)	
2 SC 2632	Si-N	=2SC2631: 1W	7c(9mm)	2SC2632	7c(9mm)	
2 SC 2633	Si-N	=2SC2631:	17j	-	-	
2 SC 2634(NC)	Si-N	Uni, ra, 60V, 0,1A, 0,4W, 200MHz	7c	BC 550	7a	
2 SC 2635(H)	Si-N	S, 650/600V, 0,1A, 0,75W, 15MHz	2a	-	-	
2 SC 2636	Si-N	UHF, 30V, 0,05A, 0,4W, 1200MHz	9c	2SC2570 A	7f	
2 SC 2637	Si-N	Vid-E, 300/300V, 0,1A, 15W, 100MHz	13j	(BF 759)	13h	5
2 SC 2644	Si-N	UHF, 25V, 0,12A, 0,5W, 4GHz	7f	-	-	
2 SC 2645	Si-N	VHF/UHF, 30V, 0,05A, 0,2W, 1200MHz	24b	BF 959	7d	
2 SC 2646	Si-N	VHF/UHF, 30V, 0,05A, 0,2W, 1200MHz	9b	BF 959	7d	
2 SC 2647	Si-N	AM/FM, 30V, 0,03A, 0,4W, 230MHz	9c	BF 255	7d	
2 SC 2650	Si-N	S-L, 500/400V, 10A, 100W, <-<3,5µs	20j	-	-	
2 SC 2653	Si-N	Vid-L, TV-VA, 350V, 0,2A, 15W, >50MHz	13j	BF 759	13h	
2 SC 2653(H)	Si-N	=2SC2653: 400/300V	13j	-	-	
2 SC 2654	Si-N	NF/S-L, 40V, 7A, 40W, <1/3,5µs	17j	BD 243 C	17j	
2 SC 2655	Si-N	NF/S, 80V, 2A, 0,9W, 100MHz	7c(9mm)	2SD1207	7c(9mm)	
2 SC 2656	Si-N	S-L, 450/450V, 7A, 80W, <1,5/4,5µs	18j	BU 426 A	18j	
2 SC 2657	Si-N	S-L, 800/500V, 1,5A, 70W, 2,5MHz	23a	BUW 11 A	18j	
2 SC 2657 A	Si-N	=2SC2657: 900/500V	23a	BUW 11 A	18j	
2 SC 2658	Si-N	S-L, 800/500V, 5A, 90W, 3MHz, <1/4µs	23a	BUW 11 A	18j	
2 SC 2658 A	Si-N	=2SC2658: 900/500V, <1,2/4,2µs	23a	BUW 11 A	18j	
2 SC 2659	Si-N	S-L, 800/500V, 7A, 120W, 3,5MHz	23a	BU 903	18j	
2 SC 2659 A	Si-N	=2SC2659: 900/500V	23a	BU 903	18j	
2 SC 2660(A)	Si-N	NF/S-L, TV-VA, 200V, 2A, 30W, 30MHz	17j	2SD1138	17j	
2 SC 2662	Si-N	NF/HF/S, 100V, 3A, 8W(Tc=25°), 50MHz	2a	-	-	
2 SC 2664	Si-N	S-L, 100/60V, 3A, 10W, 50MHz	43a	-	-	
2 SC 2665	Si-N	NF/S-L, 100V, 4A, 55W, 10MHz	18j	BD 245 C	18j	
2 SC 2668	Si-N	FM-V, 40V, 20mA, 0,1W, 550MHz	41c	BF 255	7d	
2 SC 2669	Si-N	AM/FM-ZF, 35V, 50mA, 0,2W, >100MHz	41c	BF 255	7d	