

SPS 5431	Si-P-Darl	≈MPSA 65	7e	BC 880	7c
SPS 5491	Si-P	≈BC 393	2a	MPSU 60	13m
SPU 2220	NMOS-IC	CTV, SECAM-Chroma-Prozessor	40-DIP	-	
SPU 2243	MOS-IC	CTV, SECAM-Prozessor		-	

SR 1(D....M)	Si-Di			1N4007	31a
SR 105 D	Opto	LED		-	
SRD 212	Opto			-	
SRP 10 A...K	Si-Di	≈SRP 100A...K	31a	→SRP 100A...K	
SRP 30 A...K	Si-Di	≈SRP 300A...K	31a	→SRP 300A...K	
SRP 100 A...K	Si-Di	GI, S, 50...800V, 1A, <100...200ns	31a	BYD 33M	31a
SRP 300 A...K	Si-Di	GI, S, 50...800V, 3A, <100...200ns	31a	BYW 95 C(600V)	31a
SRP 600 A...K	Si-Di	GI, S, 50...800V, 6A, <100...200ns	31a	BY 500/800	31a

SS

SS 01	Si-N	≈BC 237		BC 546	7a
SS 02	Si-N	≈BC 237		BC 546	7a
SS 100	Si-P	≈BC 307	2a	BC 556	7a
SS 101	Si-P	NF/S, -/33V, 0,05A, 0,25W	2a	(BC 556)	7a
SS 102	Si-P	≈SS 101: -/66V	2a	(BC 556)	7a
SS 106	Si-N	NF/S, 25V, 0,2A, 0,3W, <40/75ns	2a	(BC 546)	7a
SS 108	Si-N	≈SS 106: 40V	2a	(BC 546)	7a
SS 109	Si-N	≈SS 106: 20V	2a	(BC 546)	7a
SS 120	Si-N	NF/S, 60V, 0,6A, 0,8W	2a	BC 141	2a
SS 125	Si-N	NF/S, 30V, 0,5A, 0,6W	2a	BC 141	2a
SS 126	Si-N	≈SS 125: 60V	2a	BC 141	2a
SS 200	Si-N	Nix, 70V, 0,03A, 0,15W	40a	BF 420 A	7c
SS 201	Si-N	≈SS 200: 100V	40a	BF 420 A	7c
SS 202	Si-N	≈SS 200: 120V	40a	BF 420 A	7c
SS 216	Si-N	NF/S, 20V, 0,1A, 0,2W, <100/500ns	40a	(BC 546)	7a
SS 218	Si-N	≈SS 216: <35/60ns	40a	(BC 546)	7a
SS 219	Si-N	≈SS 216: 35/30ns	40a	(BC 546)	7a
SS 2648	Si-N	≈BF 258		BF 259	2a
SS 3277	Si-N	≈BF 258		BF 259	2a
SS 8050(B....D)	Si-N	NF-E, 40V, 1,5A, 1W, 190MHz	7e	2SD1207	7c
SS 8550(B....D)	Si-P	NF-E, 40V, 1,5A, 1W, 120MHz	7e	2SB892	7c(9mm)
SS 9011(D....I)	Si-N	NF, AM/FM-ZF, 50V, 0,03A, 0,4W, 370MHz	7e	BC 547, BF 255	7a, 7d
SS 9012(D....H)	Si-P	NF-E, 40V, 0,5A, 0,625W	7e	BC 327	7a
SS 9013(D....H)	Si-N	NF-E, 40V, 0,5A, 0,625W	7e	BC 337	7a
SS 9014(A....D)	Si-N	Uni, ra, 50V, 0,1A, 0,45W, 270MHz	7e	BC 550	7a
SS 9015(A....C)	Si-P	Uni, ra, 50V, 0,1A, 0,45W, 190MHz	7e	BC 560	7a
SS 9016(D....I)	Si-N	AM/FM, 30V, 25mA, 0,4W, 620MHz	7e	BF 255	7d
SS 9018(D....I)	Si-N	AM/FM, 30V, 0,05A, 0,4W, 1100MHz	7e	BF 255, BF 959	7d
SSi A16-H010	Si-Di	kV-GI, 10kV, 14mA	31a	-	
SSi A16-H012	Si-Di	≈SSi A16-H010: 12kV	31a	-	
SSi A19-H025	Si-Di	kV-GI, 25kV, 7mA	31a	-	
SSi A19-H030	Si-Di	≈SSi A19-H025: 30kV	31a	-	
SSi A19-H034	Si-Di	≈SSi A19-H025: 34kV	31a	-	
SSi B 0510	Si-Di	GI, Uni, 150V, 1,1...2,8A	27c	BY 255	31a
SSi B 0520	Si-Di	≈SSi B 0510: 300V	27c	BY 255	31a
SSi B 0540	Si-Di	≈SSi B 0510: 600V	27c	BY 255	31a
SSi B 0580	Si-Di	≈SSi B 0510: 1000V	27c	BY 255	31a
SSi B 0810	Si-Di	GI, Uni, 130V, 0,1A	31a	BA 159	31a
SSi B 0830	Si-Di	≈SSi B 0810: 400V	31a	BA 159	31a
SSi B 0850	Si-Di	≈SSi B 0810: 650V	31a	BA 159	31a