

MJE 6043	Si-N-Darl	=2N6043:	16h	(BD 901)	17j	5
MJE 6044	Si-N-Darl	=2N6044:	16h	(BD 901)	17j	5
MJE 6045	Si-N-Darl	=2N6045:	16h	(BD 901)	17j	6
MJE 8500	Si-N	S-L, 1200/700V, 2.5A, 65W, <2200/6000ns	17j	(BU 705)	18j	6*
MJE 8501	Si-N	=MJE 8500: 1400/800V	17j	(BU 705)	18j	6*
MJE 8502	Si-N	S-L, 1200/700V, 5A, 80W, <2200/6000ns	17j	(BU 908)	18j	6
MJE 8503	Si-N	=MJE 8502: 1400/800V	17j	(BU 908)	18j	6
MJE 8503 A	Si-N	=MJE 8502: 1500/700V	17j	(BU 908)	18j	6
MJE 9400	Si-N		14h	(BD 809)	17j	5
MJE 9450	Si-P	=BD 136	14h	BD 140	14h	
MJE 9780	Si-P	TV,Monitor VA, 200/150V, 3A, 40W	17j	-		
MJE 12007	Si-N	HA, 1500/750V, 2.5A, 65W	17j	(BU 705)	18j	6*
MJE 13002	Si-N	=MJ 4360:	14j	(BUX 85)	17j	6
MJE 13003	Si-N	=MJ 4361:	14j	(BUX 85)	17j	6
MJE 13004	Si-N	S-Reg, 600/300V, 4A, 75W, <800/4900ns	17j	BUT 56 A	17j	
MJE 13005	Si-N	=MJ 13004: 700/400V	17j	BUT 56 A	17j	
MJE 13006	Si-N	S-L, SMPS, 600/300V, 8A, 80W, >4MHz	17j	BUT 56 A	17j	
MJE 13007	Si-N	=MJE 13006: 700/400V	17j	BUT 56 A	17j	
MJE 13007 A	Si-N	=MJE 13006: 850/400V	17j	BUT 56 A	17j	
MJE 13008	Si-N	S-L, SMPS, 600/300V, 12A, 100W, >4MHz	17j	BUT 76 A	17j	
MJE 13009	Si-N	=MJE 13008: 700/400V	17j	BUT 76 A	17j	
MJE 13070	Si-N	HA, S-L, 650/400V, 5A, 80W	17j	BUT 11 A	17j	
MJE 13071	Si-N	=MJE 13070: 750/450V	17j	BUT 11 A	17j	
MJE 15028	Si-N	NF-L, 120V, 8A, 50W, >30MHz	17j	2SC2334	17j	
MJE 15029	Si-P	NF-L, 120V, 8A, 50W, >30MHz	17j	2SA1077	17j	
MJE 15030	Si-N	=MJE 15028: 150V	17j	-		
MJE 15031	Si-P	=MJE 15029: 150V	17j	-		
MJE 16002	Si-N	S-L, 850/450V, 5A, 80W, <400/3300ns	17j	BUT 11 A	17j	
MJE 16004	Si-N	=MJE 16002: <400/3050ns	17j	BUT 11 A	17j	
MJE 16106	Si-N	S-L, Conv., 650/400V, 8A, 100W	17j	BUF 405 A	17j	
MJE 16204	Si-N	HA, hi-res, 550/250V, 6A, 80W	17j	-		
MJE 18002	Si-N	220V= SMPS, lo-drive, 1000/450V, 2A, 50W <150/2500ns, Electronic Light Ballast	17j	-		
MJE 18002 D2	Si-N	=MJE 18002: int. Damper-Di, <150/1250ns	17j	-		
MJE 18004	Si-N	220V= SMPS, lo-drive, 1000/450V, 5A, 75W <110/2500ns, Electronic Light Ballast	17j	BUF 405 A	j	17
MJE 18004 D2	Si-N	=MJE 18004: int. Damper-Di, <150/1300ns	17j	-		
MJE 18006	Si-N	220V= SMPS, lo-drive, 1000/450V, 6A 100W, <180/2500ns, Elec. Light Ballast	17j	BUF 405 A	17j	
MJE 18008	Si-N	220V= SMPS, lo-drive, 1000/450V, 8A 125W, <180/2500ns, Elec. Light Ballast	17j	BUF 405 A	17j	
MJE 18009	Si-N	220V= SMPS, lo-drive, 1000/450V, 10A 150W, <300/2500ns, Elec. Light Ballast	17j	-		
MJE 18204	Si-N	SMPS, lo-drive, 1200/600V, 5A, 75W <200/4500ns, Electronic Light Ballast	17j	-		
MJE 18206	Si-N	SMPS, lo-drive, 1200/600V, 8A, 100W <250/4500ns, Electronic Light Ballast	17j	-		
MJE 18604	Si-N	SMPS, lo-drive, 1600/800V, 3A, 100W <900/1550ns, Electronic Light Ballast	17j	-		
MJF 122	Si-N-Darl+Di	L, 100V, 5A, 30W, B>2000, (=TIP122)	17c	2SD1415	17c	
MJF 127	Si-P-Darl+Di	L, 100V, 5A, 30W, B>2000, (=TIP127)	17c	2SB1020	17c	
MJF 2955	Si-P	L, 90V, 10A, 30W, >2Mhz, (=MJE2955)	17c	-		
MJF 3055	Si-N	L, 90V, 10A, 30W, >2Mhz, (=MJE3055)	17c	-		
MJF 6107	Si-N	L, 80V, 7A, 34W, >4MHz, (=2N6107)	17c	2SD1411	17c	
MJF 6388	Si-N-Darl+Di	L, 100V, 10A, 40W, B>3000, (=2N6388)	17c	-		