

2 N 4219	50Hz-Thy	=2N4212: 400V	2a	BRX 49	7a	
2 N 4234	Si-P	NF/S, 40V, 3A, 1W, >3MHz	2a	(BD 190)	14h	6
2 N 4235	Si-P	=2N4234: 60V	2a	(BD 190)	14h	
2 N 4236	Si-P	=2N4234: 80V	2a	(BD 190)	14h	6
2 N 4237	Si-N	NF/S, 50V, 3A, 1W, >2MHz	2a	(BD 189)	14h	6
2 N 4238	Si-N	=2N4237: 80V	2a	(BD 189)	14h	6
2 N 4239	Si-N	=2N4238: 100V	2a	(BD 189)	14h	6
2 N 4288	Si-P	NF, ra, 30V,0,05A, 0,25W, 150MHz	10b	BC 560	7a	
2 N 4289	Si-P	=2N4288: 60V	10b	2SA1124	7c(9mm)	
2 N 4316	50Hz-Thy	100V, 8A(Tc=85°), lgt/lh<15/<25mA	22a	(TAG 626-600)	17e	5
2 N 4317	50Hz-Thy	=2N4316: 200V	22a	(TAG 626-600)	17e	5
2 N 4318	50Hz-Thy	=2N4316: 300V	22a	(TAG 626-600)	17e	5
2 N 4319	50Hz-Thy	=2N4316: 400V	22a	(TAG 626-600)	17e	5
2 N 4346	Ge-P	TV-HA, 320/60V, 10A, 5W(Tc=80°)	23a	-	-	
2 N 4347	Si-N	NF/S-L, 140V, 5A, 100W, >0.2Mhz	23a	2SC3263	18j	
2 N 4391	N-FET	S, Chopper, 40V, Idss>50mA, Up<10V	2b	-	-	
2 N 4392	N-FET	S, Chopper, 40V, Idss>25mA, Up<5V	2b	-	-	
2 N 4393	N-FET	S, Chopper, 40V, Idss>5mA, Up<3V	2b	-	-	
2 N 4400	Si-N	Uni, 60V, 0,6A, 0,625W, <35/255ns,B>50	7e	BC 337	7a	
2 N 4401	Si-N	=2N4400: B>100	7e	BC 337	7a	
2 N 4402	Si-P	Uni, 40V, 0,6A, 0,625W, <35/255ns,B>50	7e	BC 327	7a	
2 N 4403	Si-P	=2N4402: B>100	7e	BC 327	7a	
2 N 4441	50Hz-Thy	50V, 5,1A(Tc=73°), lgt/lh<30/<40mA	16e	-	-	
2 N 4442	50Hz-Thy	=2N4441: 200V	16e	-	-	
2 N 4443	50Hz-Thy	=2N4441: 400V	16e	-	-	
2 N 4444	50Hz-Thy	=2N4441: 600V	16e	-	-	
2 N 4891(L)	UJT-P	Ip<5µA, Iv>2mA	7b	-	-	
2 N 4892(L)	UJT-P	=2N4891: Ip<2µA, Iv>4mA	7b	-	-	
2 N 4893(L)	UJT-P	=2N4891: Ip<2µA, Iv>2mA	7b	-	-	
2 N 4894(L)	UJT-P	=2N4891: Ip<1µA, Iv>2mA	7b	-	-	
2 N 4901	Si-P	NF/S-L, 40V, 5A, 87,5W, >4MHz, B>20	23a	BD 318	23a	
2 N 4902	Si-P	=2N4901: 60V	23a	BD 318	23a	
2 N 4903	Si-P	=2N4901: 80V	23a	BD 318	23a	
2 N 4904	Si-P	=2N4901: B>25	23a	BD 318	23a	
2 N 4905	Si-P	=2N4901: 60V, B>25	23a	BD 318	23a	
2 N 4906	Si-P	=2N4901: 80V, B>25	23a	BD 318	23a	
2 N 4916	Si-P	Uni, 30V, 0,1A, 0,2W,>400MHz,<55/180ns	8a	(BC 556)	7a	
2 N 4917	Si-P	=2N4916: >450MHz	8a	(BC 556)	7a	
2 N 4918	Si-P	NF/S-L, lo-sat, 40V, 1A, 30W, >3MHz	14h	BD 238	14h	
2 N 4919	Si-P	=2N4918: 60V	14h	BD 238	14h	
2 N 4920	Si-P	=2N4918: 80V	14h	BD 238	14h	
2 N 4921	Si-N	NF/S-L, lo-sat, 40V, 1A, 30W, >3MHz	14h	BD 237	14h	
2 N 4922	Si-N	=2N4921: 60V	14h	BD 237	14h	
2 N 4923	Si-N	=2N4921: 80V	14h	BD 237	14h	
2 N 4926	Si-N	Vid, 200V, 0,05A, 1W, >30MHz	2a	BF 259	2a	
2 N 4927	Si-N	=2N4926: 250V	2a	BF 259	2a	
2 N 5034	Si-N	NF/S-L, 55V, 6A, 83W, >0,8MHz		BD 245 C	18j	
2 N 5035	Si-N	NF/S-L, 55V, 6A, 83W, >0,8MHz		BD 245 C	18j	
2 N 5036	Si-N	=2N5034: 70V, 8A		BD 245 C	18j	
2 N 5037	Si-N	=2N5035: 70V, 8A		BD 245 C	18j	
2 N 5050	Si-N	NF/S-L, 125V, 2A, 40W, >10MHz	22a	2SD1138	17j	
2 N 5051	Si-N	=2N5050: 150V	22a	2SD1138	17j	
2 N 5052	Si-N	=2N5050: 200V	22a	2SD1138	17j	
2 N 5058(S)	Si-N	S/Vid, 300V, 0,15A, 1W, >30MHz	2a	BF 259	2a	
2 N 5059(S)	Si-N	=2N5058: 250V	2a	BF 259	2a	
2 N 5060	50Hz-Thy	30V, 0,51A(Tc=67°), lgt/lh<0,2/<5mA	7n	BRX 49	7a	