

FRH 101	Si-Di	≈1N4001		1N4007	31a
FRS 1 A...M	Si-Di	SMD, Gl, S, 50...1000V, 1A, <300ns	71a(5mm)	-	
FRS 2 A...M	Si-Di	SMD, Gl, S, 50...1000V, 1,5A, <500ns	71a(5mm)	-	
FS 1/....	Si-Di	≈RGP 10G...M		BYD 33 M	31a
FT 1 M,N,P	Si-Di	Gl, S, 140...600V, 0,3A, <3μs	31a	BA 159	31a
FT 317(A)	Si-N	≈BD 237		BD 237	14h
FT 417(A)	Si-P	≈BD 238		BD 238	14h
FT 2955	Si-P	≈BD 204	17j	BD 244 C	17j
FT 3055	Si-N	≈BD 203	17j	BD 243 C	17j
FT 5415	Si-P	≈2N5415: 0,5W	8a	MPSU 60	13m
FU 1 M,N,P	Si-Di	Gl, S, 140...600V, 0,2A, <400ns	31a	BA 159	31a
FU 12 B	Triac	100V, 3A, Igt/Ih=30/20mA	17j	TAG 232-600	17j
FU 12 C	Triac	≈FU 12B: 200V	17j	TAG 232-600	17j
FU 12 D	Triac	≈FU 12B: 300V	17j	TAG 232-600	17j
FU 12 E	Triac	≈FU 12B: 400V	17j	TAG 232-600	17j
FUF 5400	Si-Di	Gl, S, 50V, 3A, <50ns	31a	BYV 28/200	31a
FUF 5401	Si-Di	≈FUF 5400: 100V	31a	BYV 28/200	31a
FUF 5402	Si-Di	≈FUF 5400: 200V	31a	BYV 28/200	31a
FUF 5404	Si-Di	≈FUF 5400: 400V	31a	MUR 4100	31a
FUF 5406	Si-Di	≈FUF 5400: 600V	31a	MUR 4100	31a
FUF 5407	Si-Di	≈FUF 5400: 800V	31a	MUR 4100	31a
FV 1043	C-Di	≈BB 103		-	

6

G

G 1 A...M	Si-Di	Gl, Uni, 50...1000V, 1A	31a	BY 133	31a
G 2 A...M	Si-Di	Gl, Uni, 50...1000V, 2A	31a	BY 255	31a
G 2 N 2955	Si-P	≈BD 318	23a	BD 318	23a
G 2 N 3055	Si-N	≈BD 317	23a	BD 317	23a
G 3 A...M	Si-Di	Gl, Uni, 50...1000V, 3A	31a	BY 255	31a
G 4 A...M	Si-Di	Gl, Uni, 50...1000V, 3A	31a	BY 255	31a
G 5/2	Ge-Di	≈OA 70	31a	AA 138	31a
G 5/61	Ge-Di	≈AA 119	31a	AA 119	31a
G 088	Si-St	≈BZ 102/0V7	31a	(1N4148)	31a
G 580	Ge-Di	Uni, 20V, 0,2A	31a	(AA 138)	31a
G 6004	Si-P-Darl	≈BD 700	15j	BD 902	17j
G 6005	Si-N-Darl	≈BD 699	15j	BD 901	17j

GA

GA 100	Ge-Di	Uni, 26V, 0,02A	31a	AA 133	31a
GA 101	Ge-Di	Uni, 50V, 0,015A	31a	AA 133	31a
GA 102	Ge-Di	Uni, 60V, 0,012A	31a	AA 133	31a
GA 103	Ge-Di	Uni, 90V, 0,01A	31a	AA 133	31a
GA 104	Ge-Di	Uni, 115V, 0,01A	31a	AA 133	31a
GA 105	Ge-Di	Uni, 26V, 0,02A	31a	AA 133	31a
GA 106	Ge-Di	S, 35V, 0,03A(ss), 500ns	31a	AA 133	31a
GA 107	Ge-Di	S, 90V, 0,15A(ss), 500ns	31a	AA 133	31a
GA 108	Ge-Di	Uni, 90V, 0,02A	31a	AA 133	31a
(2)GA 109	Ge-Di	FM-Dem, 50V, 0,015A	31a	AA 138	31a
(2)GA 113	Ge-Di	Dem, Diskr, 35V, 0,03A(ss)	31a	AA 138	31a
GA 5005(A...T)	Si-Di	TV-Booster-Di, 6...7kV, 0,3...0,44A		-	