

Transistor Type No.	N / P / S	Manufacturer	Lead Ident	Out-line	Maximum (V)			Maximum		Max. T. (°C)	Frequency Resp. (MHz)	Leakage		Gain	
					V _{CB}	V _{CE} '	V _{EB}	I _C	Power			I _{CEO} @ V _{CB}	I _C	h _{FE} @ I _C	
2N1165	P G	MOT REN ETC	607	TU 41	80	60S	40.0	25.000A	90.000W	100J	.004E	225UA	2V	40	25.000A
2N1165A	P G	MOT REN ETC	607	TU 41	50	35S	40.0	25.000A	90.000W	100J	.004E	15MA	50V	50	25.000A
2N1166	P G	MOT REN ETC	605	TO 3	100	75S	50.0	25.000A	90.000W	100J	.004E	225UA	2V	40	25.000A
2N1166A	P G	MOT REN ETC	605	TO 3	100	75S	50.0	25.000A	90.000W	100J	.004E	15MA	100V	50	25.000A
2N1167	P G	MOT REN ETC	607	TU 41	100	75S	50.0	25.000A	100.000W	100J	.004E	225UA	2V	64	5.000A
2N1167A	P G	UEL MOT BEN ETC	607	TU 41	100	75S	50.0	25.000A	90.000W	100J	.004E	15MA	100V	50	5.000A
2N1168	P G	BEN FTC	605	TO 3	50	30R	20.0	5.000A	90.000W	100J	.004E	8MA	50V	140	1.000A
2N1169	-N G	RCA	229	TO 5	25	18	25.0	.400A	.120W	85J	4.500B	10UA	12V	40	
2N1171	P G	ETC	210	TO 5	30	12	20.0	.400A	.150W	85J	10.000B	5UA	12V	60	.001A
2N1172	P G	UEL	631	TO 37	40	16	20.0	1.500A	7.500W	100J	.017E	2MA	40V	60	
2N1175	P G	GEC MOT	212	TO 5	35	25R	10.0	.200A	.200W	85J	1.500B	12MA	30V	90	
2N1175A	P G	GEC	212	TO 5	35	25R	10.0	.200A	.200W	85J	1.500B	12UA	30V	90	.020A
2N1176	P G	ETC	210	TO 5	15	15R	10.0	.300A	.200W	100J	.015E	25UA	10V	30	
2N1176A	P G	ETC	210	TO 5	40	40R	10.0	.300A	.200W	100J	.015E	30UA	25V	30	
2N1176B	P G	ETC	210	TO 5	60	60R	10.0	.300A	.200W	100J	.015E	35UA	45V	30	
2N1177	-P G	RCA	75	TO 45	30		1.0	.010A	.080W	71A	140.004B	12UA	12V	100	
2N1178	-P G	RCA	75	TO 45	30		1.0	.010A	.080W	71A	140.004B	12UA	12V	40	
2N1179	-P G	RCA	75	TO 45	30		1.0	.010A	.080W	71A	140.000B	12UA	12V	80	
2N1180	-P G	RCA	75	TO 45	30		.0	.010A	.080W	70J	100.000G	12UA		160	.001A
2N1183	P G	RCA	171	TO 8	45	20	20.0	3.000A	1.000W	100J	.504B	250UA	45V	32	
2N1183A	P G	RCA	171	TO 8	60	30	20.0	3.000A	1.000W	100J	.504B	250UA	60V	32	
2N1183B	P G	RCA	171	TO 8	80	40	20.0	3.000A	1.000W	100J	.504B	250UA	80V	32	
2N1184	P G	RCA	171	TO 8	45	20	20.0	3.000A	1.000W	100J	.504B	250UA	45V	80	
2N1184A	P G	RCA	171	TO 8	60	20	20.0	3.000A	1.000W	100J	.504B	250UA	60V	80	
2N1184B	P G	RCA	171	TO 8	80	40	20.0	3.000A	1.000W	100J	.504B	250UA	80V	80	
2N1185	P G	ETC MOT	210	TO 5	45	30R	30.0	.500A	.200W	100J	1.750B	10UA	30V	170	.010A
2N1186	P G	ETC MOT	210	TO 5	60	45R	30.0	.500A	.200W	100J	.750B	10UA	45V	44	.010A
2N1187	P G	ETC MOT	210	TO 5	60	45R	30.0	.500A	.200W	100J	1.000B	10UA	45V	75	.010A
2N1188	P G	MOT FTC	210	TO 5	60	45R	30.0	.500A	.200W	100J	1.250B	10UA	45V	115	.010A
2N1189	P G	MOT	210	TO 5	45	30R	15.0	.500A	.200W	100J	1.750B	50UA	45V	90	.010A
2N1190	P G	MOT	210	TO 5	45	30R	15.0	.500A	.200W	100J	2.250B	50UA	45V	136	.010A
2N1191	P G	ETC MOT	210	TO 5	40	25R	25.0	.200A	.200W	85J	1.500B	15UA	25V	40	.010A
2N1192	P G	ETC MOT	210	TO 5	40	25R	25.0	.200A	.200W	85J	2.000B	15UA	25V	74	.010A
2N1193	P G	ETC MOT	210	TO 5	40	25R	25.0	.200A	.200W	85J	2.500B	15UA	25V	145	.010A
2N1194	P G	ETC MOT	210	TO 5	40	25R	25.0	.200A	.200W	85J	3.000B	15UA	25V	275	.010A
2N1195	P G	MOT	211	TO 5	30		1.0	.040A	.225W	100J	1000.000B	5UA	20V	25	.010A
2N1198	N G	ETC	210	TO 5	25	25	.5	.075A	.075W	85J	5.000B	2UA	15V	60	
2N1199	N S	ETC	211	TO 5	20	15	3.0	.100A	.300W	150J	75.000G	700NA	10V	27	.020A
2N1202	P G	SOL	427	TO 10	80	60	28.0	3.500A	34.000W	100J	.200G	2MA	80V	70	.500A
2N1203	P G	SOL	427	TO 10	120	70	28.0	3.500A	34.000W	100J	.200G	2MA	120V	44	2.000A
2N1204	P G	MOT	210	TO 5	20	15	4.0	.500A	.300W	100J	110.000G	7UA	5V	35	.400A
2N1204A	P G	MOT	210	TO 5	20	15	4.0	.500A	.300W	100J	110.000G	7UA	5V	50	.200A
2N1206	N S	ETC	210	TO 5	60	60	3.0		1.000W	200J		1UA	30V	30	.050A