

5

4

3

2

1

D

C

B

A



Description: 50 ohm BNC T Adapter
 Part No: 27-8140
 Application: Adapter
 Crimp Tool: N/A
 Impedance: 50 Ohms
 Frequency Range: 0-4 GHz
 Material: Body Brass Nickel Plated
 Contact Brass Gold Plated
 Insulator Derlin
 Crimp Sleeve Brass Nickel Plated
 Coupling Nut Zinc Nickel Plated
 RoHS Compliance: Yes
 Technical Detail: Refer to Emerson Document P/N 27-0000

DRAWING NO.
27-8140-CUST

REVISIONS

OFFICAL RELEASE

01

08-25-09 T W B Y T Betty 2009.09.08 09:28:58 +08'00'

D

C


B

A

受控 CONTROLLED DOCUMENT					
编号 P/N	27-8140-CUST	版本 Rev	01	日期 Rel'd Date	SEP 14, 09



11.1
(.437in)



36.0 ±0.5
(1.417in ±.020)

∅ 9.5
(.374in)

DIM OUTLINE

CUSTOMER COPY

TOLERANCE UNLESS OTHERWISE SPECIFIED	DRAWN BY TERRY.W	DATE 08-25-09
DECIMALS	CHECKED BY TERRY.W	DATE 08-25-09
X	APPROVED BY THOMAS	DATE 08-25-09
X.X	U/M	mm
X.XX		
ANGLES		

EMERSON
Network Power

Connectivity Solutions

TITLE
50 OHM BNC T ADAPTER

THIS DRAWING WAS PRODUCED BY COMPUTER,
DO NOT SCALE DRAWING OR UPDATE MANUALLY.

SHEET 1 OF 1	DRAWING NO. 27-8140-CUST	SIZE A
-----------------	-----------------------------	-----------

5

4

3

2

1