

2 N 5001		Si-P	=2N4999: >60MHz, hFE=70...200	{2N5000 49a	TO-59				2N5003, 2N5005, 2N5286...87
2 N 5002	USA, Tix	Si-N	S P, 100/80V, 5/10A, 50W(Tc=50°), >60MHz, 500/1300ns, hFE=30...90	49a	TO-59				2N5284...85
2 N 5003	USA, Tix	Si-P	S P, 100/80V, 5/10A, 50W(Tc=50°), >60MHz 500/1300ns, hFE=30...90	{2N5003 49a	TO-59				2N5286...87
2 N 5004		Si-N	=2N5002: >70MHz, hFE=70...200	{2N5005 49a	TO-59				2N5284...85
2 N 5005		Si-P	=2N5003: >70MHz, hFE=70...200	{2N5004 49a	TO-59				2N5286...87
2 N 5006	USA	Si-N	S P, 100/80V, 10A, 67W(Tc=60°), >30MHz, hFE=30...90	49a	TO-61				2N5288...89
2 N 5007	USA	Si-P	S P, 100/80V, 10A, 67W(Tc=100°), >30MHz, hFE=30...90	49a	TO-61				2N5290...91
2 N 5008		Si-N	=2N5006: >40MHz, hFE=70...200	{2N5009 49a	TO-61				2N5288...89
2 N 5009		Si-P	=2N5007: >40MHz, hFE=70...200	{2N5008 49a	TO-61				2N5290...91
2 N 5010	Sca, Ssi, Stc	Si-N	S, 500V, 0.5A, 4W(Tc=25°), 15MHz	2a	TO-5				BUY 59...60, 2N3439, 2N5059, 2SD793...794+
2 N 5011		Si-N	=2N5010: 600V	2a	TO-5				BUY 60, 2N5097...99, 2SC1762, 2SD594
2 N 5012		Si-N	=2N5010: 700V	2a	TO-5				2N5098...99, 2SC1762, 2SD594
2 N 5013		Si-N	=2N5010: 800V	2a	TO-5				2N5099, 2SD594
2 N 5014		Si-N	=2N5010: 900V	2a	TO-5				-
2 N 5015		Si-N	=2N5010: 1000V	2a	TO-5				-
2 N 5016	Mot, Rca, Sem Ssi, Tho, Tix	Si-N	UHF P, 65/30V, 4.5A, PQ>15W(400MHz)	49a	TO-60				-
2 N 5017	Rca	Si-N	=2N5016:		TO-217				-
2 N 5018	USA, Nsc, Tix	P-FET	Uni, 30V, Idss>10mA, Up<10V	2a	TO-18				2N3993
2 N 5019	USA, Nsc, Tix	P-FET	Uni, 30V, Idss>5mA, Up<5V	2a	TO-18				2N5116
2 N 5020	USA, Fch, Nsc	P-FET	Uni, 25V, Idss>0.3mA, Up<1.5V	2a	TO-18				2N2844
2 N 5021	USA, Fch, Nsc	P-FET	Uni, 25V, Idss>1mA, Up<2.5V	2a	TO-18				2SJ74
2 N 5022	USA, Fch, Mic Mot, Nsc	Si-P	S, 50/50V, 0.5/1A, 1W, >170MHz, <45/95ns, sat<0.4V(0.5A)	2a	TO-39				2N3468, 2SA717, 2SA742
2 N 5023	=2N5022	Si-P	=2N5022: 30/30V, >200MHz, sat<0.35V(0.5A)	2a	TO-39				2N3467...68, 2SA717, 2SA742
2 N 5024	Sca	Si-N	UHF, 20V, 15mA, 0.2W, >1300MHz	5g	TO-72				BF 377...378, BF 630, BFR 15, BFW 99, ++
2 N 5025	Fch, Tix	Si-N	HF P, 75/75V, 5A, PQ>20W(50MHz)	49a	TO-60				-
2 N 5026	Fch, Tix	Si-N	HF P, 90/90V, 5A, PQ>25W(50MHz)	49a	TO-60				-
2 N 5027	Gen, Nsc	Si-N	S, -/30V, 0.35A, 0.32W, >250MHz, <35/60ns	7c	TO-98				BSS 10...11, BSX 19...20, 2N2368...69(A), ++
2 N 5028	Gen, Nsc	Si-N	S, -/30V, 0.35A, 0.32W, >250MHz, <45/70ns	7c	TO-98				BSS 10...11, BSX 19...20, 2N2368...69(A), ++
2 N 5029	Gen, Mic, Nsc	Si-N	S, -/15V, 0.2A, 0.32W, >500MHz, <22/26ns	7c	TO-98				BSS 10...11, BSX 19...20, 2N2368...69(A), ++
2 N 5030	Gen, Mic, Nsc	Si-N	S, -/12V, 0.2A, 0.32W, >400MHz, <24/30ns	7c	TO-98				BSS 10...11, BSX 19...20, 2N2368...69(A), ++
2 N 5031	USA, Mot	Si-N	UHF, In, 15V, 0.02A, 0.2W, >1GHz	5g	TO-72				BF 377...378, BF 689, BF 763, 2N2857, ++
2 N 5032	USA, Mot	Si-N	UHF, In, 15V, 0.02A, 0.2W, >1GHz	5g	TO-72				BF 377...378, BF 689, BF 763, 2N2857, ++
2 N 5033	USA, Fch, Nsc	P-FET	Uni, 20V, Idss>0.3mA, Up<2.5V	8b	TO-106				2N2607
2 N 5034	Rca	Si-N	LFS P, 55/40V, 6/12A, 83W, >0.8MHz		TO-219A	BD 245 C	18j		BD 245, BD 545A, BDV 91, 2SC3256, ++
2 N 5035	Rca	Si-N	=2N5034:		TO-219B	BD 245 C	18j		BD 245, BD 545A, BDV 91, 2SC3256, ++
2 N 5036	Rca	Si-N	=2N5034: 70/50V, 8/12A		TO-219A	BD 245 C	18j		BD 245A, BD 545B, BDV 93, 2SC3256, ++
2 N 5037	Rca	Si-N	=2N5035: 70/50V, 8/12A		TO-219B	BD 245 C	18j		BD 245A, BD 545B, BDV 93, 2SC3256, ++
2 N 5038(-1)	USA, EUR, Tos	Si-N	S P, 150/90V, 20/30A, 140W, >60MHz, <0.5/2µs	23a	TO-3				BUV 10, BUW 57, BUX 10, BUX 40
2 N 5039(-1)		Si-N	=2N5038: 120/75V	23a	TO-3				BUV 10, BUW 57, BUX 10, BUX 40
2 N 5040	Fch	Si-P	Uni, 25/25V, 1A, 0.3W, >80MHz	2a	TO-105				BC 160...161, BC 327...328, BC 636, ++
2 N 5041	Fch	Si-P	Uni, 40/40V, 1A, 0.3W, >100MHz	2a	TO-105				BC 160...161, BC 327...328, BC 636, ++
2 N 5042	Fch	Si-P	Uni, 40V, 1A, 0.8W, >100MHz	2a	TO-39				BC 160...161, BCX 60, 2N2904...05(A), ++
2 N 5043	Ssi, Tix	Ge-P	VHF/UHF, In, 15V, 0.03A, >1500MHz	5g	TO-72				(AF 239(S))
2 N 5044	Ssi, Tix	Ge-P	VHF/UHF, In, 15V, 0.03A, >1000MHz	5g	TO-72				(AF 239(S))
2 N 5045	USA, Nsc, Tix	N-FET	Dual, 50V, Idss>0.5mA, Up<4.5V, ΔUgs<5mV	TO-71	(SDG-SDG-)				BFQ 10...16, 2N3921...22, 2N3954...58
2 N 5046		N-FET	=2N5045: ΔUgs<10mV	TO-71	(SDG-SDG-)				BFQ 10...16, 2N3921...22, 2N3954...58
2 N 5047		N-FET	=2N5045: ΔUgs<15mV	TO-71	(SDG-SDG-)				BFQ 10...16, 2N3921...22, 2N3954...58
2 N 5048	USA	Si-N	S P, 120/100V, 10/20A, 50W(Tc=100°), >10MHz	49m	TO-61				2N5288...89, 2N5542
2 N 5049	USA	Si-N	=2N5048: 60/50V	49m	TO-61				2N5288...89, 2N5542
2 N 5050	USA, Mot, Rca	Si-N	LFS P, 125/125V, 2A, 40W, >10MHz, <0.3/4.7µs	22a	TO-66	2SD1138	17j		BD 241D, BUX 67(A...C), 2N3441, 2SD1138++
2 N 5051		Si-N	=2N5050: 150/150V	22a	TO-66	2SD1138	17j		BD 241D, BUX 67(A...C), 2N3441, 2SD1138++
2 N 5052		Si-N	=2N5050: 200/200V	22a	TO-66	2SD1138	17j		BD 241F, BUX 67(A...C), 2N3583, 2SD1138++
2 N 5053	Amp, Sca, Ssi	Si-N	UHF, 30V, 0.025A, 0.2W, >1300MHz	5g	TO-72				BF 377...378, BF 630, BFR 15, BFW 99, ++
2 N 5054	Amp, Sca, Ssi	Si-N	UHF, 30V, 0.025A, 0.2W, >1500MHz	5g	TO-72				BF 377...378, BF 630, BFR 15, BFW 99, ++
2 N 5055	Fch, Nsc	Si-P	S, 12/12V, 0.1A, 0.2W, >550MHz, <25/35ns	8a	TO-106				BSX 36, 2N4313
2 N 5056	Fch, Itt, Nsc	Si-P	S, 15/15V, 0.1A, 0.36W, >600MHz, <25/45ns	2a	TO-18				BSX 36, 2N4313
2 N 5057	Fch, Itt, Nsc	Si-P	S, 15/15V, 0.1A, 0.36W, >800MHz, <25/45ns	2a	TO-18				BSX 36, 2N4313
2 N 5058(S)	USA, Mot, Tix	Si-N	S, Vid, 300/300V, 0.15A, 1W, >30MHz	2a	TO-5	BF 259	2a		BF 259, BF 659, BFS 89, BFR 59
2 N 5059(S)		Si-N	=2N5058: 250/250V	2a	TO-5	BF 259	2a		BF 258...259, BF 658...659, BFS 89, ++
2 N 5060	Gen, Mot, Tag Phi, Tix, Uni	50Hz-Thy	30V, 0.51A(Tc=67°C), 0.8A=, Igt/Ih<0.2/<5mA	7n	TO-92	BRX 49	7a		2N6564, TIC 60, MCR 100-3, BRY 55/30, ++
2 N 5061		50Hz-Thy	=2N5060: 60V	7n	TO-92	BRX 49	7a		2N6564, TIC 61, MCR 100-3, BRY 55/60, ++
2 N 5062		50Hz-Thy	=2N5060: 100V	7n	TO-92	BRX 49	7a		2N6564, TIC 62, MCR 100-3, BRY 55/100, ++
2 N 5063		50Hz-Thy	=2N5060: 150V	7n	TO-92	BRX 49	7a		2N6564, TIC 63, MCR 100-4, BRY 55/200, ++
2 N 5064		50Hz-Thy	=2N5060: 200V	7n	TO-92	BRX 49	7a		2N6564, TIC 64, MCR 100-4, BRY 55/200, ++
2 N 5065	Fch, Sca, Sgs	Si-N	S, RadH, 25/15V, 0.5A, 0.6W, >550MHz, <19/40ns	2a	=TO-5				-
2 N 5066	Tdy	Si-N	Chopper, 30/20/30V, 0.1A, 0.4W	2a	TO-46				-
2 N 5067	USA, Mot, Tix	Si-N+	LFS P, 40/40V, 5A, 87.5W, >4MHz, 0.5/2µs	{2N4901 23a	TO-3	BD 317	23a		BD 245, BDV 91, BDX 91, 2N4914...15, ++
2 N 5068		Si-N	=2N5067: 60/60V	{2N4902 23a	TO-3	BD 317	23a		BD 245A, BDV 91, BDX 91, 2N4914...15, ++
2 N 5069		Si-N	=2N5067: 80/80V	{2N4903 23a	TO-3	BD 317	23a		BD 245B, BDV 93, BDX 93, 2N5758...60, ++
2 N 5070	Mot, Rca, Sem Tix, Tho	Si-N	AM P, 65/30V, 3.3/10A, PEP=25W(30MHz)	49a	TO-60				2N5026
2 N 5071		Si-N	=2N5071: PQ>24W(76MHz)	49a	TO-60				2N5026
2 N 5072	Ssi, Tho, Trw	Si-N	S P, 100V, 10A, 125W, >40MHz						-
2 N 5073	Sca, Ssi, Tho	Si-N	Vid, 180/120V, 0.4A, 0.6W, >40MHz	2a	TO-5				BFW 36, BSS 48, 2SD413, 2SD576, 2SD624
2 N 5074	USA	Si-N	S P, 200/200V, 3A, 40W(Tc=100°), >40MHz, hFE>30	49a	TO-59				-
2 N 5075		Si-N	=2N5074: hFE=90...250	49a	TO-59				-
2 N 5076		Si-N	=2N5074: 250/250V	49a	TO-59				-
2 N 5077		Si-N	=2N5074: 250/250V, hFE=90...250	49a	TO-59				-
2 N 5078	USA, Isi, Nsc	N-FET	VHF/UHF, In, 30V, Idss>4mA, Up<8V	5n	TO-72				BF 244B...245B, BFS 72, 2N3823, 2N5398
2 N 5079	Csr, Idi, Tdy	Si-N	Uni, 60/30V, 1A, 0.36W, >400MHz, hFE=100...300	2a	TO-18				BFX 94...95, 2N3737, 2N4014
2 N 5080		Si-N	=2N5079: 200...500	2a	TO-18				BFX 94...95, 2N3737, 2N4014
2 N 5081	Csr, Idi, Tdy	Si-N	HF, 70/50V, 0.36W, >600MHz	2a	TO-18				-
2 N 5082		Si-N	=2N5081: 60/30V	2a	TO-18				-
2 N 5083	USA	Si-N	S P, 120/60V, 10A, 25W(Tc=100°), hFE=40...120	49a	TO-59				(2N5288...89, 2N5542)¶
2 N 5084		Si-N	=2N5083: hFE=100...300	49a	TO-59				(2N5288...89, 2N5542)¶
2 N 5085		Si-N	=2N5083: 150/80V	49a	TO-59				(2N5542)¶