

2 N 6265	Rca	Si-N	UHF Drv,Out, 50V, 0,275A, PQ>2W(2GHz)	62a	-	-	-	-	-	-
2 N 6266	Rca	Si-N	UHF P, 50V, 1A, PQ>5W(2GHz)	62a	-	-	-	-	-	-
2 N 6267	Rca	Si-N	UHF P, 50V, 1,5A, PQ>10W(2GHz)	62a	-	-	-	-	-	-
2 N 6268	Rca	Si-N	UHF Drv,Out, 45V, 0,35A, PQ>2W(2,3GHz)	62a	-	-	-	-	-	-
2 N 6269	Rca	Si-N	UHF P, 45V, 1,5A, PQ>6,5W(2,3GHz)	62a	-	-	-	-	-	-
2 N 6270	USA,Tix	Si-N	S P, 100/80V, 30/40A, 150W(Tc=100°), >75MHz	23a	TO-3					2N5671
2 N 6271		Si-N	=2N6270: 120/100V	23a	TO-3					2N5671
2 N 6272		Si-N	=2N6270:	49m	TO-63					2N2824...25
2 N 6273		Si-N	=2N6270: 120/100V	49m	TO-63					2N2825
2 N 6274	Mot,Ker,Ssi Stc	Si-N	S P, 120/100V, 50/100A, 250W, >30MHz, -/ <1050ns hFE=30...120	23a	TO-3					2N6032...33
				{2N6378						
2 N 6275		Si-N	=2N6274: 140/120V	23a	TO-3					2N6033
2 N 6276		Si-N	=2N6274: 160/140V	23a	TO-3					-
2 N 6277		Si-N	=2N6274: 180/150V	23a	TO-3					-
2 N 6278		Si-N	=2N6274:	49m	TO-63					-
2 N 6279		Si-N	=2N6274: 140/120V	49m	TO-63					-
2 N 6280		Si-N	=2N6274: 160/140V	49m	TO-63					-
2 N 6281		Si-N	=2N6274: 180/150V	49m	TO-63					-
2 N 6282	USA,Lbd,Mot Rca,Sgs	Si-N-Darl+Di	L.F.S P, 60/60V, 20/40A, 160V, >4MHz, hFE=750...18k	23a	TO-3					BDX 69(A...C), MJ 11012, 2SD730, 2SD1460
				{2N6285						
2 N 6283		Si-N-Darl+Di	=2N6282: 80/80V	23a	TO-3					BDX 69A...C, MJ 11014, 2SD730, 2SD1460
2 N 6284		Si-N-Darl+Di	=2N6282: 100/100V	23a	TO-3					BDX 69B...C, MJ 11016, 2SD730, 2SD1460
2 N 6285	USA,Lbd,Mot Rca,Sgs	Si-P-Darl+Di	L.F.S P, 60/60V, 20/40A, 160W, >4MHz, hFE=750...18k	23a	TO-3					BDX 68(A...C), MJ 11011, 2SB694
				{2N6282						
2 N 6286		Si-P-Darl+Di	=2N6285: 80/80V	23a	TO-3					BDX 68A...C, MJ 11013, 2SB694
2 N 6287		Si-P-Darl+Di	=2N6285: 100/100V	23a	TO-3					BDX 68B...C, MJ 11015, 2SB694
2 N 6288	Fer,Mic,Mot Nsc,Rca,Sgs	Si-N	L.F.S P, 40/30V, 7/10A, 40W, >4MHz	{2N6111	17j	TO-220AB	BD 809	17j		BD 243, BD 543, BD 795, BD 805, ++
2 N 6289		Si-N	=2N6288:	{2N6110	17j	TO-220AA	BD 809	17j		BD 243, BD 543, BD 795, BD 805, ++
2 N 6290		Si-N	=2N6288: 60/50V	{2N6109	17j	TO-220AB	BD 809	17j		BD 243A, BD 543A, BD 797, BD 807, ++
2 N 6291		Si-N	=2N6288: 60/50V	{2N6108	17j	TO-220AA	BD 809	17j		BD 243A, BD 543A, BD 797, BD 807, ++
2 N 6292		Si-N	=2N6288: 80/70V	{2N6107	17j	TO-220AB	BD 809	17j		BD 243B, BD 543B, BD 799, BD 809, ++
2 N 6293		Si-N	=2N6288: 80/70V	{2N6106	17j	TO-220AA	BD 809	17j		BD 243B, BD 543B, BD 799, BD 809, ++
2 N 6294	Mot,Stc	Si-N-Darl+Di	L.F.S P, 60/60V, 4/8A, 50W, >4MHz, hFE>750	{2N6296	22a	TO-66				BD 645, BD 897, BDW 23A, BDW 63A, ++
2 N 6295		Si-N-Darl+Di	=2N6294, 80/80V	{2N6297	22a	TO-66				BD 647, BD 899, BDW 23B, BDW 63B, ++
2 N 6296	Mot,Stc	Si-P-Darl+Di	L.F.S P, 60/60V, 4/8A, 50W, >4MHz, hFE>750	{2N6264	22a	TO-66				BD 646, BD 898, BDW 24A, BDW 64A, ++
2 N 6297		Si-P-Darl+Di	=2N6296: 80/80V	{2N6265	22a	TO-66				BD 648, BD 900, BDW 24B, BDW 64B, ++
2 N 6298	Mot,Stc	Si-P-Darl+Di	=2N6053: 75W	{2N6300	22a	TO-66				BD 646, BD 898, BDW 74A, BDX 54A, ++
2 N 6299	Mot,Stc	Si-P-Darl+Di	=2N6054: 75W	{2N6301	22a	TO-66				BD 648, BD 900, BDW 74B, BDX 54B, ++
2 N 6300	Mot,Stc	Si-N-Darl+Di	=2N6055: 75W	{2N6298	22a	TO-66				BD 645, BD 897, BDW 73A, BDX 53A, ++
2 N 6301	Mot,Stc	Si-N-Darl+Di	=2N6056: 75W	{2N6299	22a	TO-66				BD 647, BD 899, BDW 73B, BDX 53B, ++
2 N 6302	Ker,Stc,Tix	Si-N	S P, 140/120V, 16A, 150W, >0,2MHz	23a	TO-3					BD 745E, BDX 50, 2N3773, 2SC2608
2 N 6303	USA,Mot,Sgs	Si-P	S, 80/80V, 3/10A, 1W, >60MHz, <100/400ns	2a	TO-39					
2 N 6304	Mot,Sca	Si-N	UHF, 30/15V, 0,05A, 0,2W, >1400MHz	5g	TO-72					BFS 55, BFR 37, BFW 30, BFX 73, ++
2 N 6305	Mot,Sca	Si-N	UHF, 30/15V, 0,05A, 0,2W, >1200MHz	5g	TO-72					BFS 55, BFR 37, BFW 30, BFX 73, ++
2 N 6306	USA,Mot,Rca Tix	Si-N	S P, 500/250V, 8/16A, 125W, >5MHz, -/ <1200ns hFE=15...75	23a	TO-3					BUS 12(A), BUW 25...26, BUW 34...36, ++
2 N 6307		Si-N	=2N6306: 600/300V	23a	TO-3					BUS 12(A), BUW 25...26, BUW 35...36, ++
2 N 6308		Si-N	=2N6306: 700/350V	23a	TO-3					BUS 12(A), BUW 26, BUW 35...36, ++
2 N 6309	Mot	Si-N	S P, 120/100V, 90A, 400W, >30MHz, -/ <1250ns	49m	TO-114					
2 N 6310		Si-N	=2N6309: 140/120V	49m	TO-63					
2 N 6311		Si-N	=2N6309: 160/140V	49m	TO-63					
2 N 6312	USA,Mot	Si-P	L.F.S P, 40/40V, 5/10A, 75W, >4MHz	{2N4231A	22a	TO-66				BD 244, BD 540, BD 948, 2SB550, ++
2 N 6313		Si-P	=2N6312: 60/60V	{2N4232A	22a	TO-66				BD 244A, BD 540A, BD 950, 2SB550, ++
2 N 6314		Si-P	=2N6312: 80/80V	{2N4233A	22a	TO-66				BD 244B, BD 540B, BD 952, 2SB550, ++
2 N 6315	Mot,Ssi,Stc	Si-N	=2N5873: 90W	{2N6317	22a	TO-66				BD 543A, BD 797, BD 807, 2N5428...30, ++
2 N 6316		Si-N	=2N5874: 90W	{2N6318	22a	TO-66				BD 543B, BD 799, BD 809, 2N5428...30, ++
2 N 6317		Si-P	=2N5871: 90W	{2N6315	22a	TO-66				BD 544A, BD 798, BD 808, 2N5954...55, ++
2 N 6318		Si-P	=2N5872: 90W	{2N6316	22a	TO-66				BD 544B, BD 800, BD 810, 2N5954, ++
2 N 6319	Mot	Si-N	S P, 120/100V, 80A, 300W, >30MHz, -/1250ns							
2 N 6320	Mot	Si-N	=2N6319: 140/120V							
2 N 6321	Mot	Si-N	=2N6319: 160/140V							
2 N 6322	USA,Tix	Si-N	S P, 300/200V, 30/40A, 350W, >10MHz, 800/-ns	23a	TO-3					BUR 21...22, BUV 22...23, BUX 22...23, ++
2 N 6323		Si-N	=2N6322: 400/300V	23a	TO-3					BUV 23, BUX 23
2 N 6324		Si-N	=2N6322:	49m	TO-63					-
2 N 6325		Si-N	=2N6322: 400/300V	49m	TO-63					-
2 N 6326	USA,Tix	Si-N	P, 60/60V, 30/40A, 200W, >3MHz, 600/900ns	{2N6329	23a	TO-3				BDY 29, MJ 802, 2N6270...72, 2SD797
2 N 6327		Si-N	=2N6326: 80/80V	{2N6330	23a	TO-3				BDY 29, MJ 802, 2N6270...72, 2SD797
2 N 6328		Si-N	=2N6326: 100/100V	{2N6331	23a	TO-3				BDY 29, MJ 802, 2N6270...72, 2SD797
2 N 6329	USA,Tix	Si-P	P, 60/60V, 30/40A, 200W, >3MHz, 600/900ns	{2N6326	23a	TO-3				MJ 4502
2 N 6330		Si-P	=2N6329: 80/80V	{2N6327	23a	TO-3				MJ 4502
2 N 6331		Si-P	=2N6329: 100/100V	{2N6328	23a	TO-3				MJ 4502
2 N 6332	Tag,Tix	50Hz-Thy	30V, 2A(Tc=80°), Igt/Ih<0,2/<5mA	2a	TO-39					TAG 615-100, (C 106Y, TAG 106Y,++) <sup>4</sup>
2 N 6333		50Hz-Thy	=2N6332: 50V	2a	TO-39					TAG 615-100, (C 106F, TAG 106F,++) <sup>4</sup>
2 N 6334		50Hz-Thy	=2N6332: 100V	2a	TO-39					TAG 615-100, (C 106A, TAG 106A,++) <sup>4</sup>
2 N 6335		50Hz-Thy	=2N6332: 200V	2a	TO-39					TAG 615-200, (C 106B, TAG 106B,++) <sup>4</sup>
2 N 6336		50Hz-Thy	=2N6332: 300V	2a	TO-39					TAG 615-400, (C 106C, TAG 106C,++) <sup>4</sup>
2 N 6337		50Hz-Thy	=2N6332: 400V	2a	TO-39					TAG 615-400, (C 106D, TAG 106D,++) <sup>4</sup>
2 N 6338	USA,Mot,Tix	Si-N	S P, 120/100V, 25/50A, 200W, >40MHz, -/ <1250ns	23a	TO-3					BDW 30, 2N5671...72, 2N6272, 2N6274...77
2 N 6339		Si-N	=2N6338: 140/120V	{2N6438	23a	TO-3				BDW 30, BDY 58, 2N5672, 2N6275...77
2 N 6340		Si-N	=2N6338: 160/140V	23a	TO-3					BDW 32, BDY 58, 2N6276...77
2 N 6341		Si-N	=2N6338: 180/150V	23a	TO-3					BDW 34, 2N6277
2 N 6342	Mot,Rca,Tag	Triac	200V, 8A=(Tc=80°), Igt/Ih<50/<40mA	17j	TO-220					T2802B, MAC222-4, TIC226B, TXD10K40, ++
2 N 6342 A		Triac	=2N6342: 12A=(Tc=80°)	17j	TO-220					TIC236B, TW11N400, TXD10K40P, MAC15-4, ++
2 N 6343		Triac	=2N6342: 400V	17j	TO-220					T2802D, MAC222-6, TIC226D, TXD10K40, ++
2 N 6343 A		Triac	=2N6343: 12A=(Tc=80°)	17j	TO-220					TIC236D, TW11N400, TXD10K40P, MAC15-6, ++
2 N 6344		Triac	=2N6342: 600V	17j	TO-220					T2802M, MAC222-8, TIC226M, TXD10K60, ++
2 N 6344 A		Triac	=2N6344: 12A=(Tc=80°)	17j	TO-220					TIC236M, TW11N600, TXD10K60P, MAC15-8, ++
2 N 6345		Triac	=2N6342: 800V	17j	TO-220					T2802N, MAC222-10, TIC226N, TXD10K80, ++
2 N 6345 A		Triac	=2N6345: 12A=(Tc=80°)	17j	TO-220					TIC236N, TW11N800, TXD10K80P, MAC15-10, ++
2 N 6346	Mot,Rca,Tix	Triac	200V, 8A=(Tc=80°), Igt/Ih<75/<40mA	17j	TO-220					TAG224-200, MAC222A-4, BT137/500, ++
2 N 6346 A		Triac	=2N6346: 12A=(Tc=80°)	17j	TO-220					BT138/500, TAG255-200, TXD10H40P, ++
2 N 6347		Triac	=2N6346: 400V	17j	TO-220					TAG224-400, MAC222A-6, BT137/500, ++