

TRANSISTOR NUMBER	PM OA LT	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE	MFR	EUR EQUIV	USA EQUIV	ISS
2N3448	NS	T03	L05	100V	80V	10V	7A	200C	115WC	10M	400P	40/120	5A	RHG	MOB	BDY24	2N3448	0
2N3449	PG	T018	L01	15V	6V		100MA	100C	150MWF	300M	5P	20M	10MA	VLS	OBS	ASZ21	2N964	2
2N3450	NS	T05	L04	120V	60V		800MA	200C	600MWF	100M	15P	40/120	150MA	RMH	OBS	BFT39	2N3723	2
2N3451	PS	T018	L01	6V	6V	4V	200MA	200C	300MWF	500M	5P5	30/120	10MA	VLS	OBS	BSW25	2N3546	0
2N3461	PG	T05	L04	60V	30V		3A	110C	5WC			90/150	500MA	AHG	OBS	AD132/5	2N1543	2
2N3462	NS	T018	L01	50V	35V		30MA	200C	300MWF	10M	6P	100MN	10UA	ALN	OBS	BC107C	2N2484	2
2N3463	NS	T018	L01	60V	45V		30MA	200C	300MWF	45M	6P	120MN	10UA	ALN	OBS	BC107C	2N2484	2
2N3464	NS	T05	L04	60V	40V		5A	200C	5WC	30M		35/100	200MA	RHP	TRW	BSV64	2N5784	2
2N3467	PS	T05	L04	40V	40V	5V	1A	200C	1WF	175M	25P	40/120	500MA	AMG	MOB	BFS95	2N4036	2
2N3467S	PS	T039	L04	40V	40V		1A	200C	1WF	175M	25P	40/120	500MA	AMG	MOU	BFS95	2N4036	2
2N3468	PS	T05	L04	50V	50V	5V	1A	200C	1WF	150M	25P	25/75	500MA	VMS	MOB		2N3468	2
2N3468S	PS	T039	L04	50V	50V	5V	1A	200C	1WF	150M	25P	25/75	500MA	VMS	MOU	BFR23	2N3245	2
2N3469	NS	T05	L04	35V	25V		5A	200C	1.2WC	20M		100MN	500MA	RHP	TRW	BSV64	2N5154	2
2N3470	NS	T063	L60	50V	50V		10A	150C	150WC	500K		100MN	10A	AHD	OBS			2
2N3471	NS	T063	L60	100V	100V		10A	150C	150WC	500K		100MN	10A	AHD	OBS			2
2N3472	NS	T063	L60	150V	150V		10A	150C	150WC	500K		100MN	10A	AHD	OBS			2
2N3473	NS	T063	L60	200V	200V		10A	150C	150WC	500K		100MN	10A	AHD	OBS			2
2N3474	NS	T063	L60	50V	50V		10A	150C	150WC	500K		400MN	10A	AHD	OBS			2
2N3475	NS	T063	L60	100V	100V		10A	150C	150WC	500K		400MN	10A	AHD	OBS			2
2N3476	NS	T063	L60	150V	150V		10A	150C	150WC	500K		400MN	10A	AHD	OBS			2
2N3477	NS	T063	L60	220V	200V		10A	150C	150WC	500K		400MN	10A	AHD	OBS			2
2N3478	NS	T072	L06	30V	15V	2V	50MA	175C	200MWF	750M	1P	25MN	2MA	VLA	NAT	BFY90	2N3933	2
2N3485	PS	T046	L01	60V	40V	5V	600MA	200C	400MWF	200M	8P	40/120	150MA	RMG	MOB	BSW24	2N2907A	0
2N3485A	PS	T046	L01	60V	60V	5V	600MA	200C	400MWF	200M	8P	40/120	150MA	RMG	MOB	BSW24	2N2907A	0
2N3486	PS	T046	L01	60V	40V	5V	600MA	200C	400MWF	200M	8P	100MN	150MA	RMG	MOB	BSW24	2N2907A	0
2N3487	NS	T061	L46	80V	60V	10V	7A	200C	117WC	10M	550P	20/60	3A	RHG	MOB	BDY63	2N1725	0
2N3488	NS	T061	L46	100V	80V	10V	7A	200C	117WC	10M	550P	20/60	3A	RHH	MOB	BDY63	2N1725	0
2N3489	NS	T061	L46	120V	100V	10V	7A	200C	117WC	10M	550P	15/45	3A	RHH	MOB	BDY63	2N1725	0
2N3490	NS	T061	L46	80V	60V	10V	7A	200C	11MWC	10M	550P	40/120	5A	RHG	MOB	BDY63	2N1725	0
2N3491	NS	T061	L46	100V	80V	10V	7A	200C	117WC	10M	550P	40/120	5A	RHH	MOB	BDY63	2N1725	0
2N3492	NS	T061	L46	120V	100V	10V	7A	200C	117WC	10M	550P	30/90	5A	RHH	MOB	BDY63	2N1725	0
2N3493	NS	T072	L06	12V	8V		25MA	200C	150MWF	400M	0P7	40/120	500UA	ULA	OBS		2N3839	2
2N3494	PS	T05	L04	80V	80V	4V	100MA	200C	600MWF	200M	7P	40MN	50MA	ALH	MOB		2N4928	0
2N3495	PS	T05	L04	120V	120V	4V	100MA	200C	600MWF	150M	6P	40MN	50MA	ALH	MOB		2N4928	0
2N3496	PS	T018	L01	80V	80V	4V	100MA	200C	400MWF	200M	7P	40MN	50MA	ALH	MOB	BSV68	2N3497	0
2N3497	PS	T018	L01	120V	120V	4V	100MA	175C	400MWF	150M	6P	40MN	10MA	ALH	MOB	BSV68	2N3497	0
2N3498	NS	T05	L04	100V	100V	6V	500MA	200C	1WF	150M	10P	40/120	150MA	AMH	MOB	BSW66	2N1893	0
2N3498S	NS	T039	L04	100V	100V	6V	500MA	200C	1WF	150M	10P	40/120	150MA	AMH	MOB	BSW66	2N1893	2
2N3499	NS	T05	L04	100V	100V	6V	500MA	200C	1WF	150M	10P	100MN	150MA	AMH	MOB	BSW66	2N1893	0
2N3499S	NS	T039	L04	100V	100V	6V	500MA	200C	1WF	150M	10P	100MN	150MA	AMH	MOB	BSW66	2N1893	2
2N3500	NS	T05	L04	150V	150V	6V	300MA	200C	1WF	150M	8P	40/120	150MA	AME	MOB	BSW67	2N5682	0
2N3501	NS	T05	L04	150V	150V	6V	300MA	200C	1WF	150M	8P	100MN	150MA	AME	MOB	BSW67	2N5682	0
2N3502	PS	T05	L04	45V	45V	5V	600MA	180C	700MWF	200M	8P	115MN	50MA	RMG	SGI	BSW54	2N2219A	0
2N3503	PS	T05	L04	60V	60V	5V	600MA	180C	700MWF	200M	8P	115MN	50MA	RMG	SGI	BSW54	2N2219A	0
2N3504	PS	T018	L01	45V	45V	5V	600MA	180C	400MWF	200M	8P	115MN	50MA	RMG	SGI	BSW24	2N2907A	0
2N3505	PS	T018	L01	60V	60V	5V	600MA	180C	400MWF	200M	8P	115MN	50MA	RMG	SGI	BSW24	2N2907A	0
2N3506	NS	T039	L04	60V	40V	5V	3A	200C	1WF	60M	40P	30/150	1500MA	VMS	MOB	BSX59	2N3725	0
2N3507	NS	T039	L04	80V	50V	5V	3A	200C	1WF	60M	40P	40/700	1500MA	VMS	MOB	BSX59	2N3725	0
2N3508	NS	T046	L01	40V	20V	6V	500MA	200C	400MWF	500M	4P	40/120	10MA	UMS	MOB	BSX20	2N2369	0
2N3509	NS	T046	L01	40V	20V	6V	500MA	200C	400MWF	500M	4P	100MN	10MA	UMS	MOB	BSX20	2N2369	0
2N3510	NS	T018	L01	40V	10V	6V	500MA	200C	360MWF	350M	4P	25/150	150MA	VLS	MOB	BSX20	2N2369	0
2N3511	NS	T018	L01	40V	15V	6V	500MA	200C	360MWF	450M	4P	30/120	150MA	VLS	MOB	BSX20	2N2369	0
2N3526	NS	T05	L04	130V	120V	5V	200MA	175C	800MWF	40M	12P	30MN	30MA	AMH	SGI	BSW66	2N1893	0
2N3527	PS	T046	L01	30V	30V		100MA	200C	400MWF	5M	10P	25/75	0.1UA	ALN	OBS	BC390	2N2484	2
2N3543	NS	T03	L05	65V	60V	4V	5A	175C	60WC	150M	100P	10/80	4A5	AHS	TRW	BDX91	2N5069	2
2N3544	NS	T018	L01	25V		3V	100MA	175C	400MWF	600M	2P5	25MN	10MA	ULP	MOB			0
2N3545	PS	T018	L01	20V	20V	5V	200MA	200C	360MWF	250M	8P	40/120	10MA	RLS	NAT	BSW24	2N2907A	0
2N3546	PS	T018	L01	15V	12V	4V	200MA	200C	360MWF	700M	6P	30MN	10MA	ULS	MOB	BSW25	2N3546	0
2N3547	PS	T018	L01	60V	60V	6V	100MA	175C	400MWF	45M	8P	100MN	1MA	ALG	NAT	BC177	2N3965	0
2N3548	PS	T018	L01	60V	45V	6V	100MA	175C	400MWF	60M	8P	100MN	10UA	ALN	NAT	BC179	2N3965	0
2N3549	PS	T018	L01	60V	60V	6V	100MA	175C	400MWF	60M	8P	100MN	10UA	ALN	NAT	BC179	2N3965	0
2N3550	PS	T018	L01	60V	45V	10V	100MA	175C	400MWF	60M	8P	200MN	10UA	ALN	NAT	BC179	2N3965	0
2N3551	NS	X49	X49	115V	60V	7V	12A	175C	40WC	40M		20/90	10A	RHP	TIB			1
2N3552	NS	X49	X49	140V	80V	7V	40M		40WC	40M		20/90	10A	RHP	TIB			1
2N3553	NS	T039	L04	65V	40V	4V	1A	200C	7WC	250M	10P	10MN	250MA	UMP	MOB	BSS14	2N3735	0
2N3554	NS	T039	L04	60V	30V	5V	1A2	200C	800MWF	150M	25P	25/100	750MA	RMS	OBS	BSS14	2N3735	2
2N3563	NS	T0106	L17	30V	12V	2V	50MA	125C	200MWF	600M	1P7	30/200	1MA	VLA	FCU	BFX73	2N918	0
2N3564	NS	T0106	L17	30V	15V	4V	100MA	125C	200MWF	400M	3P5	20/500	15MA	VLA	FCU	BFX73	2N918	0
2N3565	NS	T0106	L17	30V	25V	6V	50MA	125C	200MWF	40M	4P	70MN	100UA	ALN	SGI	BC209	2N4967	0
2N3566	NS	T0105	L04	40V	30V	5V	200MA	125C	300MWF	40M	25P	150MN	10MA	ALG	SGI	BC107	A157	0
2N3567	NS	T0105	L04	80V	40V	5V	500MA	125C	300MWF	60M	20P	40/120	150MA	AMG	SGI	BFY50	2N2297	0
2N3568	NS	T0105	L04	80V	60V	5V	500MA	125C	300MWF	60M	20P	40/120	150MA	AMG	SGI	BFY50	2N2297	0
2N3569	NS	T0105	L04	80V	40V	5V	500MA	125C	300MWF	60M	20P	100MN	150MA	AMG	SGI	BFY50	2N2297	0
2N3570	NS	T072	L06	30V	15V	3V	50MA	200C	200MWF	1500M	0P75	20/150	5MA	ULA	SEU			0