

2 N 4437		Si-N	=2N4436: hFE=100...220	8a	TO-106	BC 337A, BC 637, BSV 59, 2N2221...22(A), ++
2 N 4438	Sca, Ssi, Sty	Si-N	Vid, 300/300V, 0.2A, 1W, >30MHz, hFE=40...120	2a	TO-39	BF 259, BF 659, BFR 59, BFS 89, 2N5058
2 N 4439		Si-N	=2N4438: hFE=100...240	2a	TO-39	BF 259, BF 659, BFR 59, BFS 89, 2N5058
2 N 4440	USA, Rca, Mot Tho, Tix, ++	Si-N	VHF/UHF P, 65/40V, 1.5A, PQ<5W(400MHz)	49a	TO-60	-
2 N 4441	Mot	50Hz-Thy	50V, 5.1A(Tc=73°), 8A=, Igt/Ih<30/<40mA	16e	TO-127	-
2 N 4442		50Hz-Thy	=2N4441: 200V	16e	TO-127	-
2 N 4443		50Hz-Thy	=2N4441: 400V	16e	TO-127	-
2 N 4444		50Hz-Thy	=2N4441: 600V	16e	TO-127	-
2 N 4445	Tix, Tdy	N-FET	S, Chopper, 25V, 0.4A, Up<10V	2b	TO-46	-
2 N 4445 A		N-FET	=2N4445: 35V	2b	TO-46	-
2 N 4446	Tix, Tdy	N-FET	S, Chopper, 25V, 0.4A, Up<5V	2b	TO-46	-
2 N 4446 A		N-FET	=2N4446: 35V	2b	TO-46	-
2 N 4447	Tix, Tdy	N-FET	S, Chopper, 20V, 0.4A, Up<5V	2b	TO-46	-
2 N 4447 A		N-FET	=2N4447: 25V	2b	TO-46	-
2 N 4448	Tix, Tdy	N-FET	S, Chopper, 20V, 0.4A, Up<5V	2b	TO-46	-
2 N 4448 A		N-FET	=2N4448: 25V	2b	TO-46	-
2 N 4449	Fch, Ray, Sca	Si-N	S, -15V, 0.2A, 0.3W, >500MHz, <69/20ns	2a	TO-46	BSS 11...12, BSX 19...20, 2N2368...69(A), ++
2 N 4450	Fch, Mot, Sgs	Si-N	Uni, 60/30V, 0.5A, 0.36W, 350MHz, 50/125ns	2a	TO-46	BC 337A, BC 637, BSV 59, 2N2221...22(A), ++
2 N 4451	Fch, Sgs	Si-P	S, -12V, 0.1A, 0.3W, >400MHz, <65/95ns	2a	TO-46	BSX 36, 2N4313, 2N3209, 2N4125...26, ++
2 N 4452	Fch, Sca, Sgs	Si-P	S, 45/45V, 0.6A, 0.35W, >200MHz, <95/210ns	2a	TO-46	BC 327, BC 638, BSW 24, 2N2906...07(A), ++
2 N 4453	Fch, Mot, Sgs	Si-P	Uni, 25/18V, 0.2A, 0.3W, >400MHz, 30/60ns	2a	TO-46	BC 308, BC 558, BSW 24, 2N3250...51(A), ++
2 N 4576		Si-N	S P, 100V, 150W			-
2 N 4851	Mot, Tix	UJT-P	35/30V, 50mA, iEM=1.5A, 0.3W, Ip<2µA, Iv>2mA, η=0.56...0.75, Rbb=4.7...9.1kΩ	5e	TO-72	2N4947, 2N4948, 2N4893
2 N 4852		UJT-P	=2N4851: Iv>4mA, η=0.7...0.85	5e	TO-72	2N4892
2 N 4853		UJT-P	=2N4851: Ip<0.4µA, Iv>6mA, η=0.7...0.85	5e	TO-72	-
2 N 4854	Mot, Sgs, Tix	Si-N/P	NPN+PNP, 60/40V, 0.6A, 0.6W, >200MHz, hFE=100...300	TO-77	(CBE-EBC-)	BFX 79
2 N 4855		Si-N/P	=2N4854: hFE=40...120	TO-77	(CBE-EBC-)	BFX 79
2 N 4856(A)	USA, EUR	N-FET	S, sym, 40V, Idss>50mA, Up<10V	2b	TO-18	BFS 74, BFS 77, BSV 78, 2N3970, 2N4391
2 N 4857(A)	USA, EUR	N-FET	S, sym, 40V, Idss>20mA, Up<6V	2b	TO-18	BFS 75, BFS 78, BSV 79
2 N 4858(A)	USA, EUR	N-FET	S, sym, 40V, Idss>8mA, Up<4V	2b	TO-18	BFS 76, BFS 79, BSV 80, 2N4093
2 N 4859(A)	USA, EUR	N-FET	S, sym, 30V, Idss>50mA, Up<10V	2b	TO-18	BFS 74, BFS 77, BSV 78, 2N3970, 2N4391
2 N 4860(A)	USA, EUR	N-FET	S, sym, 30V, Idss>20mA, Up<6V	2b	TO-18	BFS 75, BFS 78, BSV 79
2 N 4861(A)	USA, EUR	N-FET	S, sym, 30V, Idss>8mA, Up<4V	2b	TO-18	BFS 76, BFS 79, BSV 80, 2N4093
2 N 4862	USA	Si-N	LFS, 140/120V, 2A, 4W(Tc=100°), >50MHz	2a	TO-46	(BUX 49, BUY 41, 2SC1860) <sup>6</sup>
2 N 4863	USA	Si-N	LFS, 140/120V, 2A, 7W(Tc=25°), >50MHz	2a	TO-5	(BUX 49, BUY 41, 2SC1860) <sup>6</sup>
2 N 4864	USA	Si-N	LFS P, 140/120V, 2A, 29W, >50MHz	22a	TO-66	2SC2529, 2SC2660, 2SD759...760
2 N 4865	USA	Si-N	S P, 100/80V, 90A, 350W, >10MHz	49m	TO-114	2N6309...11
2 N 4866		Si-N	=2N4865: 140/120V	49m	TO-114	2N6309...11
2 N 4867(A)	Isi, Tix, ++	N-FET	Uni, In, 40V, Idss>0.4mA, Up<2V	5k	TO-72	2N4339, 2N5358, 2SK83, 2SK193, 2SK195
2 N 4868(A)	Isi, Tix, ++	N-FET	Uni, In, 40V, Idss>3mA, Up<3V	5k	TO-72	BC 264, BF 410, 2SK192, 2SK370
2 N 4869(A)	Isi, Tix	N-FET	Uni, In, 40V, Idss>2.5mA, Up<6V	5k	TO-72	BF 256, BFS 71, 2N3822, 2N4221, ++
2 N 4870	Mot, Phi	UJT-P	35/30V, 50mA, iEM=1.5A, 0.3W, Ip<5µA, Iv>2mA, η=0.56...0.75, Rbb=4...9.1kΩ	7b	TO-92	2N4891
2 N 4871		UJT-P	=2N4870: Iv>4mA, η=0.7...0.85	7b	TO-92	2N2646
2 N 4872	Fch, Sgs	Si-P	S, RadH, 12/12V, 0.05A, 0.3W, >900MHz, <25/30ns	2a	TO-18	-
2 N 4873	Fch, Sgs	Si-N	S, RadH, 40/15V, 0.2A, 0.36W, >700MHz, <20/30ns	2a	TO-18	-
2 N 4874	Ray, Sca, Tix	Si-N	VHF/UHF Os, Drv, 30V, 0.2A, 0.72W, >900MHz	2a	TO-39	BFR 36, 2SC1199, 2SC1252, 2SC1365...66
2 N 4875	Ray, Sca, Tix	Si-N	VHF/UHF Os, Drv, 40V, 0.2A, 0.72W, >800MHz	2a	TO-39	BFR 36, 2SC1199, 2SC1252, 2SC1365...66
2 N 4876	Ray, Sca, Tix	Si-N	VHF/UHF Os, Drv, 40V, 0.2A, 0.72W, >650MHz	2a	TO-39	BFR 36, 2SC1199, 2SC1252, 2SC1365...66
2 N 4877	USA, Mot	Si-N	LFS, 70/60V, 4A, 10W(Tc=25°), >30MHz	2a	TO-39	BUX 34, BUY 80, 2N5336...39
2 N 4878	Isi, Sol, Sty	Si-N	=2N4044: 0.5W	TO-71	(CBE-EBC-)	>2N4044
2 N 4879	Isi, Sol, Sty	Si-N	=2N4100: 0.5W	TO-71	(CBE-EBC-)	>2N4100
2 N 4880	Isi, Sol, Sty	Si-N	=2N4045: 0.5W	TO-71	(CBE-EBC-)	>2N4045
2 N 4881	Tdy, Tix, Tsc	N-FET	S, 300V, Idss>0.4mA, Up<15V	2b	TO-5	2N5543
2 N 4882	Tdy, Tix, Tsc	N-FET	S, 300V, Idss>1.5mA, Up<15V	2b	TO-5	2N5543
2 N 4883	Tdy, Tix, Tsc	N-FET	S, 200V, Idss>0.4mA, Up<15V	2b	TO-5	2N5542...43
2 N 4884	Tdy, Tix, Tsc	N-FET	S, 200V, Idss>1.5mA, Up<15V	2b	TO-5	2N5542...43
2 N 4885	Tdy, Tix, Tsc	N-FET	S, 125V, Idss>0.4mA, Up<15V	2b	TO-5	2N5542...43
2 N 4886	Tdy, Tix, Tsc	N-FET	S, 125V, Idss>1.5mA, Up<15V	2b	TO-5	2N5542...43
2 N 4888	Fch, Spe	Si-P	Vid, 150/150V, 0.05A, 0.3W, >30MHz, hFE=40...400	8a	TO-105	BF 398, BF 423, BF 435...437, 2SC1370, ++
2 N 4889		Si-P	=2N4888: >40MHz, hFE=80...300	8a	TO-105	BF 398, BF 423, BF 435...437, 2SC1370, ++
2 N 4890(Si)	USA, Mot	Si-P	LFS, 60/40V, 0.5A, 1W, 280MHz, 35/130ns	2a	TO-5	BC 161, BC 303...304, 2N2904...05(A), ++
2 N 4891(L)	Mot, Tix	UJT-P	30V, 50mA, iEM=1A, 0.3W, Ip<5µA, Iv>2mA, η=0.55...0.82, Rbb=4...9.1kΩ (2N4891...94L)	7b	SOT-30	2N4870
2 N 4892(L)		UJT-P	=2N4891: Ip<2µA, Iv>4mA, η=0.51...0.69	7b	SOT-30	2N4852
2 N 4893(L)		UJT-P	=2N4891: Ip<2µA, Iv>2mA, η=0.55...0.82, Rbb=4...12kΩ	7b	SOT-30	2N4851, 2N4947, 2N4948
2 N 4894(L)		UJT-P	=2N4891: Ip<1µA, Iv>2mA, η=0.74...0.86, Rbb=4...12kΩ	7b	SOT-30	2N4949
2 N 4895	USA, Sgs	Si-N	S, 120/60V, 5A, 1W, >50MHz, hFE=40...120	2a	TO-39	BFT 34, BUX 34, BUY 80
2 N 4896		Si-N	=2N4895: >80MHz, B=100...300	2a	TO-39	BFT 34, BUX 34, BUY 80
2 N 4897		Si-N	=2N4895: 150/80V	2a	TO-39	BUY 80
2 N 4898	USA, Fch, Mot Rca, Sgs, Tix	Si-P	LFS P, 40/40V, 1/4A, 25W, >3MHz, sat<0.6V(1A) hFE=20...100 (2N4910)	22a	TO-66	BD 240, BD 242, BDX 14, 2N3740...41, ++
2 N 4899		Si-P	=2N4898: 60/60V (2N4911)	22a	TO-66	BD 240A, BD 242A, BDX 14, 2N3740...41, ++
2 N 4900		Si-P	=2N4898: 80/80V (2N4912)	22a	TO-66	BD 240B, BD 242B, BDX 14, 2N3741, ++
2 N 4901	USA, Fch, Mot Tho, Tix	Si-P	LFS P, 40/40V, 5/15A, 87.5W, >4MHz, sat<1.5V(5A) hFE=20...80 (2N5067)	23a	TO-3	BD 246, BDV 92, BDX 92, 2N5871...72, ++
2 N 4902		Si-P	=2N4901: 60/60V (2N5068)	23a	TO-3	BD 246A, BDV 92, BDX 92, 2N5871...72, ++
2 N 4903		Si-P	=2N4901: 80/80V (2N5069)	23a	TO-3	BD 246B, BDV 94, BDX 94, 2N5872, ++
2 N 4904		Si-P	=2N4901: hFE=25...100 (2N4913)	23a	TO-3	BD 246, BDV 92, BDX 92, 2N5871...72, ++
2 N 4905		Si-P	=2N4901: 60/60V, hFE=25...100 (2N4914)	23a	TO-3	BD 246A, BDV 92, BDX 92, 2N5871...72, ++
2 N 4906		Si-P	=2N4901: 80/80V, hFE=25...100 (2N4915)	23a	TO-3	BD 246B, BDV 94, BDX 94, 2N5872, ++
2 N 4907	USA, Sgs	Si-P	LFS P, 40/40V, -10A, 150W, 4MHz, sat<2V(10A)	23a	TO-3	BD 312, BD 546, BDW 22, 2N5875...76, ++
2 N 4908		Si-P	=2N4907: 60/60V	23a	TO-3	BD 312, BD 546A, BDW 22A, 2N5875...76, ++
2 N 4909		Si-P	=2N4907: 80/80V	23a	TO-3	BD 314, BD 546B, BDW 22B, 2N5876, ++
2 N 4910	USA, Fch, Mot Tho, Tix	Si-N	LFS P, 40/40V, 1/4A, 25W, >3MHz, sat<0.6V(1A) hFE=20...100 (2N4898)	22a	TO-66	BD 239, BD 241, BDY 78, 2N4231...33, ++
2 N 4911		Si-N	=2N4910: 60/60V (2N4899)	22a	TO-66	BD 239A, BD 241A, BDY 78, 2N4232...33, ++
2 N 4912		Si-N	=2N4910: 80/80V (2N4900)	22a	TO-66	BD 239B, BD 241B, BDY 78, 2N4233, ++
2 N 4913	USA, Fch, Mot Rca, Tx	Si-N	LFS P, 40/40V, 5/15A, 87.5W, >4MHz, sat<1.5V(5A) hFE=25...100 (2N4904)	22a	TO-66	BD 245, BDV 91, BDX 91, 2N5873...74, ++
2 N 4914		Si-N	=2N4913: 60/60V (2N4905)	22a	TO-66	BD 245A, BDV 91, BDX 91, 2N5873...74, ++