

2 N 3901	USA, Mic, Nsc	Si-N	Uni, 18V, 0,1A, 0,36W, 200MHz	7c	TO-98			BC 168, BC 183, BC 238, BC 548, ++
2 N 3902	USA, Mot, Tix	Si-N	S P, 700/325V, 2,5A, 100W(Tc=75°)	23a	TO-3			BUS 11(A), BUX 46(A), 2SC3091, 2SC3155
2 N 3903	USA, EUR	Si-N	Uni, 60V, 0,2A, 0,625W, >250MHz, hFE=50...150	7e	TO-92	BC 546	7a	BC 174, BC 182, BC 190, BC 546, ++
2 N 3904		Si-N	=2N3903: hFE=100...300	7e	TO-92	BC 546	7a	BC 174, BC 182, BC 190, BC 546, ++
2 N 3905	USA, EUR	Si-P	Uni, 40V, 0,2A, 0,625W, >200MHz, hFE=50...150	7e	TO-92	BC 556	7a	BC 212, BC 257, BC 307, BC 557, ++
2 N 3906		Si-P	=2N3905: hFE=100...300	7e	TO-92	BC 556	7a	BC 212, BC 257, BC 307, BC 557, ++
2 N 3907	USA, Mic, Nsc	Si-N	Dual, 60V, 0,03A, 0,6W, >60MHz, hFE=60...300	TO-77	(CBE-EBC-)			BFY 81, 2N2919...20
2 N 3908		Si-N	=2N3907: hFE=100...500	TO-77	(CBE-EBC-)			BFY 81, 2N2919...20
2 N 3909(A)	USA, Mot, Tix	P-FET	Uni, 20V, Idss>0,3mA, Up<8V	5n	TO-72			BF 320, 2N3820, 2N5800
2 N 3910	USA	Si-P	Chopper, 60/50/50V, 0,2A, 0,5W	2a	TO-46			-
2 N 3911		Si-P	Chopper, 60/40/40V, 0,2A, 0,5W	2a	TO-46			-
2 N 3912	USA	Si-P	Chopper, 60/30/30V, 0,2A, 0,5W	2a	TO-46			-
2 N 3913		Si-P	=2N3910: 0,4W	2a	TO-18			-
2 N 3914		Si-P	=2N3911: 0,4W	2a	TO-18			-
2 N 3915		Si-P	=2N3912: 0,4W	2a	TO-18			-
2 N 3916	USA	Si-N	S, Vid, 150/150V, 0,15A, 5W, >50MHz	43m	=TO-37			{BF 380, BF 415, MJE 340, 2SC2376, ++}†
2 N 3917	USA, Tix	Si-N	S P, 80V, 2A, 20W(Tc=45°), >80MHz, hFE=30...120	23a	TO-3			2SC1195
2 N 3918		Si-N	=2N3917: hFE=100...300	23a	TO-3			2SC1195
2 N 3919	USA, Tix	Si-N	S P, 120V, 10A, 15W(Tc=75°), >80MHz, hFE=40...120	23a	TO-3			BUW 70, BUY 55, 2SC2769
2 N 3920		Si-N	=2N3919: hFE=100...300	23a	TO-3			BUW 70, BUY 55, 2SC2769
2 N 3921	USA, Isi, Nsc	N-FET	Dual, In, 50V, Idss>1mA, Up<3V	TO-71	(SDG-SDG-)			BFQ 10...16, 2N3954...59
2 N 3922	USA, Isi, Nsc	N-FET	Dual, In, 50V, Idss>1mA, Up<3V	TO-71	(SDG-SDG-)			BFQ 10...16, 2N3954...59
2 N 3923	USA, Fch	Si-N	Vid, 150/150V, 0,05A, 0,8W, >40MHz	2a	TO-5			BF 257...259, BF 657...659, 2N5058...59, ++
2 N 3924	Mot, Phi, Sem Tho, Tix, Val	Si-N	VHF Drv, Out, 36/18V, 0,5A, PQ=4W(175MHz)	2a	TO-39			BFS 22, BFW 46, BLY 33, MRF 237
2 N 3925	Mot	Si-N	VHF Drv, Out, 36V, 1A, PQ=5W(175MHz)	49m	TO-102			BLY 55, BLY 57, BLY 78
2 N 3926	=2N3924	Si-N	VHF P, 36V, 1,5A, PQ=7W(175MHz)	49a	TO-60			BLW 35, BLY 58
2 N 3927	=2N3924	Si-N	VHF P, 36V, 3A, PQ=12W(175MHz)	49a	TO-60			BLY 58
2 N 3928	Idi, Sol, Tix	Si-N	S, 80V, 3A, 5W(Tc=25°), >200MHz, <35/75ns	2a	TO-5			2N3507
2 N 3929		Si-N	=2N3928: 20W	49m	TO-59			-
2 N 3930	Fch, Sca, Sgs	Si-P	Vid, 180/180V, 0,05A, 0,4W, >40MHz	2a	TO-18	BF 421 A	7c	BF 436...437, BF 491...493, 2SA1370...71, ++
2 N 3931		Si-P	=2N3930: 0,7W	2a	TO-39	MPS-U606	13m	BFQ 36...37, BFT 44...45, 2SB606, ++
2 N 3932	USA, Mic, Rca	Si-N	VHF/UHF, 30V, 0,2W, >750MHz	5g	TO-104			BF 377...378, BF 689, BF 763, 2N2857, ++
2 N 3933	USA, Mic, Rca	Si-N	VHF/UHF, 40V, 0,2W, >750MHz	5g	TO-104			BF 377...378, BF 689, BF 763, 2N2857, ++
2 N 3934	Nsc, Tsc	N-FET	Dual, In, 50V, Idss>0,3mA, Up<3V	TO-71	(SDG-SDG-)			BFQ 10...16, 2N3954...59
2 N 3935	Nsc, Tsc	N-FET	Dual, In, 50V, Idss>0,3mA, Up<3V	TO-71	(SDG-SDG-)			BFQ 10...16, 2N3954...59
2 N 3936	Ssi, Tag, Tix	50Hz-Thy	100V, 7A(Tc=80°), IgV/Ih<60<110mA	21b	TO-64			BTW 42/600R, TAG 9N400, TAG 15-100, ++
2 N 3937		50Hz-Thy	=2N3936: 200V	21b	TO-64			BTW 42/600R, TAG 9N400, TAG 15-200, ++
2 N 3938		50Hz-Thy	=2N3936: 300V	21b	TO-64			BTW 42/600R, TAG 9N400, TAG 15-300, ++
2 N 3939		50Hz-Thy	=2N3936: 400V	21b	TO-64			BTW 42/600R, TAG 9N400, TAG 15-400, ++
2 N 3940		50Hz-Thy	=2N3936: 500V	21b	TO-64			BTW 42/600R, TAG 9N600, TAG 15-500, ++
2 N 3941	Sol, Sty	Si-N	Dual, 60/45V, 0,05A, 0,75W, >200MHz, hFE=400 ΔhFE=0,9...1, ΔUbe<3mV	TO-77	(CBE-EBC-)			2N3409...11
2 N 3942		Si-N	=2N3941: ΔhFE=0,8...1, ΔUbe<10mV	TO-77	(CBE-EBC-)			2N3409...11
2 N 3943		Si-N	=2N3941:	TO-71	(EBC-EBC-)			-
2 N 3944		Si-N	=2N3942:	TO-71	(EBC-EBC-)			-
2 N 3945	USA, Mic, Nsc	Si-N	Uni, 70V, 1A, 5W(Tc=25°), >60MHz	2a	TO-5			BC 140...141, 2N1990, 2N2102, 2N2405, ++
2 N 3946	USA, Mic, Mot	Si-N	LFS, 60V, 0,2A, 0,36W, <70/375ns, hFE=50...150	2a	TO-18			BC 182, BC 546, 2N2221...22(A), ++
2 N 3947		Si-N	=2N3946: hFE=100...300	2a	TO-18			BC 182, BC 546, 2N2221...22(A), ++
2 N 3948	USA, Mot, Tix	Si-N	UHF A, Os, Drv, 36V, 0,4A, PQ=1W(400MHz)	2a	TO-39			BFS 50, MRF 629, 2SC2762, 2SC3185
2 N 3950	USA, Mot	Si-N	AM/FM P, 65V, 3,3A, PQ=50W(50MHz)	49a	TO-60			-
2 N 3953	Sca, Ssi	Si-N	UHF, 15V, 0,03A, 0,2W, >1300MHz	5g	TO-72			BF 377...378, BF 698, BF 763, 2N2857, ++
2 N 3954(A)	USA, Nsc, Tix	N-FET	Dual, VHF, In, 50V, Idss>0,5mA, Up<4,5V	TO-71	(SDG-SDG-)			BFQ 10...16, 2N3921...22
2 N 3955(A)	USA, Nsc, Tix	N-FET	Dual, VHF, In, 50V, Idss>0,5mA, Up<4,5V	TO-71	(SDG-SDG-)			BFQ 10...16, 2N3921...22
2 N 3956	USA, Nsc, Tix	N-FET	Dual, VHF, In, 50V, Idss>0,5mA, Up<4,5V	TO-71	(SDG-SDG-)			BFQ 10...16, 2N3921...22
2 N 3957	USA, Nsc, Tix	N-FET	Dual, VHF, In, 50V, Idss>0,5mA, Up<4,5V	TO-71	(SDG-SDG-)			BFQ 10...16, 2N3921...22
2 N 3958	USA, Nsc, Tix	N-FET	Dual, VHF, In, 50V, Idss>0,5mA, Up<4,5V	TO-71	(SDG-SDG-)			BFQ 10...16, 2N3921...22
2 N 3959	USA, Mot	Si-N	SS, 20V, 0,03A, 0,4W, 5,4/4,9ns	2a	TO-18			-
2 N 3960	USA, Mot	Si-N	SS, 20V, 0,03A, 0,4W, 5,4/4,9ns	2a	TO-18			-
2 N 3961	USA, Mot	Si-N	VHF Drv, Out, 65V, 1A, PQ=4W(175MHz)	49m	TO-102			BLY 60
2 N 3962	USA, EUR	Si-P	LF, In, 60V, 0,2A, 0,36W, >40MHz	2a	TO-18			2SA970, 2SA1049, 2SA1136...37
2 N 3963	USA, EUR	Si-P	LF, In, 80V, 0,2A, 0,36W, >40MHz	2a	TO-18			2SA970, 2SA1049, 2SA1136...37
2 N 3964	USA, EUR	Si-P	LF, In, 45V, 0,2A, 0,36W, >50MHz	2a	TO-18			BC 416, BC 560, 2SA970, 2SA1136...37, ++
2 N 3965	USA, EUR	Si-P	LF, In, 60V, 0,2A, 0,36W, >50MHz	2a	TO-18			2SA970, 2SA1049, 2SA1136...37
2 N 3966	USA, EUR, Mic	N-FET	S, 30V, Idss>2mA, Up<6V, <120/100ns	5k	TO-72			BFS 76, BFS 79
2 N 3967(A)	USA, Nsc	N-FET	Uni, 30V, Idss>2,5mA, Up<6V	5k	TO-72			BF 256A, BFS 71, 2N3822, 2N4221, ++
2 N 3968(A)	USA, Nsc	N-FET	Uni, 30V, Idss>1mA, Up<3V	5k	TO-72			BFW 12, 2N4340, 2N5484
2 N 3969(A)	USA, Nsc	N-FET	Uni, 30V, Idss>0,4mA, Up<1,7V	5k	TO-72			2N4339, 2N5358, 2SK83, 2SK195, 2SK238
2 N 3970	USA, Mot, Tix	N-FET	S, Chopper, 40V, Idss>50mA, Up<10V	2b	TO-18			BFS 74, BFS 77...78, 2N4391, 2N4856
2 N 3971	USA, Mot, Tix	N-FET	S, Chopper, 40V, Idss>25mA, Up<5V	2b	TO-18			2N4392, 2N5434
2 N 3972	USA, Mot, Tix	N-FET	S, Chopper, 40V, Idss>5mA, Up<3V	2b	TO-18			2N4393
2 N 3973	Gen, Sem, Spr	Si-N	LFS, 60V, 0,4A, 0,36W, <60/110ns	7c	TO-98			BSV 59, BSX 49, 2N2221...22(A), 2N4014, ++
2 N 3974	Gen, Sem, Spr	Si-N	LFS, 60V, 0,4A, 0,36W, <60/110ns	7c	TO-98			BSV 59, BSX 49, 2N2221...22(A), 2N4014, ++
2 N 3975	Gen, Sem, Spr	Si-N	LFS, 60V, 0,4A, 0,36W, <60/200ns	7c	TO-98			BSV 59, BSX 49, 2N2221...22(A), 2N4014, ++
2 N 3976	Gen, Sem, Spr	Si-N	LFS, 60V, 0,4A, 0,36W, <60/200ns	7c	TO-98			BSV 59, BSX 49, 2N2221...22(A), 2N4014, ++
2 N 3977	Spr, Ssi	Si-P	Chopper, 15/10/15V, 0,1A, 0,4W	2a	TO-46			2N2944
2 N 3978	USA, Mot	Si-P	Chopper, 25/20/25V, 0,1A, 0,4W	2a	TO-46			2N2945
2 N 3979	Spr, Ssi, Tdy	Si-P	Chopper, 40/35/40V, 0,1A, 0,4W	2a	TO-46			2N2946
2 N 3980	Mot, Tix	UJT-P	35/30V, 50mA, IEM=1A, 0,36W, Ip<2μA, Iv>1mA, η=0,68...0,82, Rbb=4...8kΩ	5e	TO-72			-
2 N 3981	Nsc, Sty	Si-N	S, 60V, 1A, 0,8W, >250MHz, <35/40ns	2a	TO-5			BSS 27, BSV 77, BSV 95, 2N5189, +++
2 N 3982	Nsc, Sty	Si-N	S, 50V, 1A, 0,8W, >250MHz, <30/40ns	2a	TO-5			BSS 27, BSV 77, BSV 95, 2N5189, +++
2 N 3983	Sem, Sty	Si-N	VHF, 30V, 0,03A, 0,2W, >500MHz	7c	TO-92			BF 225, BF 310, BF 314, BF 502, BF 505++
2 N 3984	Sem, Sty	Si-N	VHF, 30V, 0,03A, 0,2W, >400MHz	7c	TO-92			BF 225, BF 310, BF 314, BF 502, BF 505++
2 N 3985	Sem, Sty	Si-N	VHF, 30V, 0,03A, 0,2W, >300MHz	7c	TO-92			BF 225, BF 310, BF 314, BF 502, BF 505++
2 N 3993(A)	USA, Mot, Tix	P-FET	S, Chopper, 25V, Idss>10mA, Up<9,5V	5n	TO-72			MPF 970
2 N 3994(A)	USA, Mot, Tix	P-FET	S, Chopper, 25V, Idss>2mA, Up<5,5V	5n	TO-72			MPF 971
2 N 3995	Tix	Ge-P	VHF, 20V, 0,1A, 0,3W, >600MHz	2a	TO-39			2N2929
2 N 3996	USA, Tix	Si-N	S P, 100V, 5A, 30W(Tc=100°), >40MHz	50g	TO-111			2N5002, 2N5004, 2N5284...85
2 N 3997	USA, Tix	Si-N	S P, 100V, 5A, 30W(Tc=100°), >40MHz	50g	TO-111			2N5002, 2N5004, 2N5284...85
2 N 3998	USA, Tix	Si-N	S P, 100V, 5A, 30W(Tc=100°), >40MHz	=49m	TO-111a			2N5002, 2N5004, 2N5284...85
2 N 3999	USA, Tix	Si-N	S P, 100V, 5A, 30W(Tc=100°), >40MHz	=49m	TO-111a			2N5002, 2N5004, 2N5284...85
2 N 4000	USA, Tix	Si-N	S, 100V, 1A, 15W(Tc=100°), >40MHz	2a	TO-5			BUX 49, BUY 41