

2 N 4231 A		Si-N	=2N4231: 5A, 75W	[2N6312	22a	TO-66		BD 243, BD 949, BD 539A, 2N3054, ++	
2 N 4232		Si-N	=2N4231: 70/60V		22a	TO-66		BD 241A, BD 537, BD 539B, 2N3054, ++	
2 N 4232 A		Si-N	=2N4231: 5A, 75W	[2N6313	22a	TO-66		BD 243A, BD 951, BD 539B, 2N3054, ++	
2 N 4233		Si-N	=2N4231: 90/80V		22a	TO-66		BD 241B, BD 937, BD 539C, 2N3054, ++	
2 N 4233 A		Si-N	=2N4231: 90V	[2N6314	22a	TO-66		BD 243B, BD 953, BD 539C, 2N3054, ++	
2 N 4234	USA, Mot, Mic Sgs, Tix, ++	Si-P	LFS, 40/40V, 3A, 1W, >3MHz, sat<0.6V(1A)	[2N4237	2a	TO-5	(BD 190) ⁶	14h	BFT 35...37, BSS 46, 2N6190...93
2 N 4235		Si-P	=2N4234: 60/60V	[2N4238	2a	TO-5	(BD 190)	14h	BFT 35...37, BSS 46, 2N6190...93
2 N 4236		Si-P	=2N4234: 80/80V	[2N4239	2a	TO-5	(BD 190) ⁶	14h	BFT 35...37, BSS 46, 2N6190...93
2 N 4237	=2N4234	Si-N	LFS, 50/40V, 3A, 1W, >2MHz, sat<0.6V(1A)	[2N4234	2a	TO-5	(BD 189) ⁶	14h	BFT 32...34, BSS 63...64, 2N5336...39
2 N 4238		Si-N	=2N4237: 80/60V		2a	TO-5	(BD 189) ⁶	14h	BFT 32...34, BSS 63...64, 2N5336...39
2 N 4239		Si-N	=2N4238: 100/80V		2a	TO-5	(BD 189) ⁶	14h	BFT 33...34, BSS 64, 2N5338...39, 25C2214
2 N 4240	Mot, Rca, Sem Tho, Tix	Si-N	S P, 500/300V, 2/5A, 35W, >15MHz, <500/9000ns		22a	TO-66			BUW 40A, BUX 84, 2N3585, 25C3169, ++
2 N 4241(MP)	USA	Ge-P	LF P, 32, 5A, 37W		23a	TO-3			AL 102...103, AUJ 28, 2N3611...18, ++
2 N 4242	Csr, Sem	Ge-P	LFS P, 80, 10A, 106W, hFE=40...80		23a	TO-3			2N1559...60, 2N2289...90, 2N2292...93, ++
2 N 4243		Ge-P	=2N4242: 60V		23a	TO-3			2N1558...60, 2N2289...90, 2N2292...93, ++
2 N 4244		Ge-P	=2N4242: 40V		23a	TO-3			2N1557...60, 2N2288...90, 2N2291...93, ++
2 N 4245		Ge-P	=2N4242: hFE=60...120		23a	TO-3			2N1559...60, 2N2289...90, 2N2292...93, ++
2 N 4246		Ge-P	=2N4242: 60V, hFE=60...120		23a	TO-3			2N1558...60, 2N2289...90, 2N2292...93, ++
2 N 4247		Ge-P	=2N4242: 40V, hFE=60...120		23a	TO-3			2N1557...60, 2N2288...90, 2N2291...93, ++
2 N 4248	USA, Mic, Sgs	Si-P	Uni, 40/40V, 0.1A, 0.2W, hFE>50		8a	TO-106			BC 415...416, BC 560, 2SA970, 2SA1137, ++
2 N 4249		Si-P	=2N4248: 60/60V, hFE=100...300		8a	TO-106			2SA970, 2SA1049, 2SA1136...37
2 N 4250		Si-P	=2N4248: hFE=250...700		8a	TO-106			BC 415...416, BC 560, 2SA970, 2SA1137, ++
2 N 4250 A		Si-P	=2N4248: 60/60V, hFE=250...700		8a	TO-106			2SA970, 2SA1049, 2SA1136...37
2 N 4251	Fch, Ssi	Si-N	SS, RadH, 15/10V, 0.1A, 0.25W, >1300MHz, <20/60ns		2a	TO-46			-
2 N 4252	USA, Tix	Si-N	AM/FM Imp, Mx, Os, 30V, 0.05A, >600MHz, hFE>50		5g	TO-72			BF 240...241, BF 254...255, BF 594...595, ++
2 N 4253		Si-N	=2N4252: hFE=30...150		5g	TO-72			BF 240...241, BF 254...255, BF 594...595, ++
2 N 4254		Si-N	=2N4252: 0.25W		7c	TO-92			BF 240...241, BF 254...255, BF 594...595, ++
2 N 4255		Si-N	=2N4252: 0.25W, hFE=30...150		7c	TO-92			BF 240...241, BF 254...255, BF 594...595, ++
2 N 4256	Gen, Sem, Spr	Si-N	S, 30V, 0.1A, 0.36W, 200MHz, 4/40ns		7c	TO-98			BSS 11...12, BSX 19...20, 2N2368...69(A), ++
2 N 4257(A)	USA, Nsc, Sgs	Si-P	S, 6/6V, 0.05A, 0.2W, >500MHz		8a	TO-106			BSX 36
2 N 4258(A)	USA, Nsc, Sgs	Si-P	S, 12/12V, 0.05A, 0.2W, >700MHz		8a	TO-106			BSX 36
2 N 4259	USA, Nsc, Rca	Si-N	UHF, 40/40V, 0.175W, 1GHz		5g	TO-72			BF 377...378, BF 689, BF 763, 2N2857, ++
2 N 4260	USA, Mot, Tix	Si-P	SS, 15/15V, 0.03A, 0.2W, >1.6GHz, 1.5/2ns		5g	TO-72			-
2 N 4261		Si-P	=2N4260: >2GHz		5g	TO-72			-
2 N 4262	Mot, Sty	Si-N	HF Drv, Out, 25V, 0.2A, >900MHz		49a	TO-102			-
2 N 4263		Si-N	=2N4262		49a	TO-102			-
2 N 4264	Fch, Mot, Spr	Si-N	S, 30V, 0.2A, 0.625W, <23/35ns, hFE=40...160		7e	TO-92			BSS 10...11, BSX 19...20, 2N2368...69(A), ++
2 N 4265		Si-N	=2N4264: hFE=100...400		7e	TO-92			BSS 10...11, BSX 19...20, 2N2368...69(A), ++
2 N 4266		Si-N	=2N4264: hFE=40...400		7e	TO-92			BSS 10...11, BSX 19...20, 2N2368...69(A), ++
2 N 4267	Fch, Isi, Tdy	MOS-P-FET-e	S, 30V, Idss<1nA, Up<6V		5(DGsubS)	TO-72			-
2 N 4268	Fch, Isi, Tdy	MOS-P-FET-e	S, 30V, Idss<1nA, Up<6V		5(DGsubS)	TO-72			-
2 N 4269	Csr, Sem, Tra	Si-N	Nixie, 200V, 0.03A, 0.36W		2a	TO-18			BF 298...299, BF 422, 25C3467
2 N 4270		Si-N	=2N4269: 0.2W		2a	TO-5			BF 258...259, BF 658...659, 2N5058...59, ++
2 N 4271	USA	Si-N	S, 175/140V, 1A, 5W(Tc=100°), >20MHz		2a	TO-5			BSS 48...49, BUX 50...52, 2N3439...40, ++
2 N 4272	USA	Si-N	S, 175/140V, 2.5A, 5W(Tc=100°), >10MHz		2a	TO-5			BUX 50...52, 25C1861...62, 25D625
2 N 4273	USA	Si-N	S P, 175/140V, 2.5A, 25W, >10MHz		22a	TO-66			BD 241F, BUX 67, 25D386(A), 25D1138, ++
2 N 4274	USA, Nsc, Sgs	Si-N	SS, 30/12V, 0.1A, 0.2W, >400MHz, <12/12ns		8a	TO-106			BSV 91...92, BSX 92...93, 2N2368...69(A), ++
2 N 4275		Si-N	=2N4274: 40/15V		8a	TO-106			BSV 91...92, BSX 92...93, 2N2368...69(A), ++
2 N 4276	Gpd, Mot	Ge-P	LFS P, 30/20V, 60A, 170W, hFE=60...180		23a	TO-3			2N5435...40
2 N 4277		Ge-P	=2N4276: hFE=120...240		23a	TO-3			2N5435...40
2 N 4278		Ge-P	=2N4276: 45/30V		23a	TO-3			2N5435...40
2 N 4279		Ge-P	=2N4276: 45/30V, hFE=120...240		23a	TO-3			2N5435...40
2 N 4280		Ge-P	=2N4276: 60/45V		23a	TO-3			2N5435...40
2 N 4281		Ge-P	=2N4276: 60/45V, hFE=120...240		23a	TO-3			2N5435...40
2 N 4282		Ge-P	=2N4276: 75/60V		23a	TO-3			2N5435...40
2 N 4283		Ge-P	=2N4276: 75/60V, hFE=120...240		23a	TO-3			2N5435...40
2 N 4284	Nsc, Pih	Si-P	LF, sym, 25/25/25V, 0.05A, 0.25W		10b				-
2 N 4285		Si-P	=2N4284: 35/35/35V		10b				-
2 N 4286	Nsc, Pih	Si-N	LF, 30V, 0.05A, 0.25W		10b				BC 168, BC 183, BC 238, BC 548, ++
2 N 4287		Si-N	=2N4286: 45V		10b				BC 167, BC 182, BC 237, BC 547, ++
2 N 4288	Nsc, Pih	Si-P	LF, In, 30V, 0.05A, 0.25W, 150MHz		10b		BC 560	7a	BC 214, BC 259, BC 309, BC 559, ++
2 N 4289		Si-P	=2N4288: 60V		10b		2SA1124	7c(9mm)	2SA872(A), 2SA970, 2SA1049, 2SA1137, ++
2 N 4290	Mic, Nsc, Pih	Si-P	LF, In, 30V, 0.2A, 0.25W, 150MHz		10b				BC 214, BC 259, BC 309, BC 559, ++
2 N 4291		Si-P	=2N4290: 40V		10b				BC 415...416, BC 560, 2SA872(A), 2SA970, ++
2 N 4292	Mic, Nsc, Pih	Si-N	VHF, IF, 30V, 0.06A, 0.2W, 730MHz		10b				BF 225, BF 314, BF 502, BF 505, BF 507, ++
2 N 4293	Mic, Nsc, Pih	Si-N	VHF, IF, 30V, 0.06A, 0.2W, 730MHz		10b				BF 225, BF 314, BF 502, BF 505, BF 507, ++
2 N 4294	Mic, Nsc	Si-N	S, 30V, 0.2A, 0.2W, <21/30ns		10b				BSS 10...11, BSX 19...20, 2N2368...69(A), ++
2 N 4295	Mic, Nsc	Si-N	S, 40V, 0.2A, 0.2W, <24/30ns		10b				BSS 10...11, BSX 19...20, 2N2368...69(A), ++
2 N 4296	USA, Rca	Si-N	S P, 350/250V, 1A, 20W, >20MHz, hFE=50...150		22a	TO-66			BUW 40(A,B), TIP 47...50, 2N4240, ++
2 N 4297		Si-N	=2N4296: hFE=75...300		22a	TO-66			BUW 40(A,B), TIP 47...50, 2N4240, ++
2 N 4298		Si-N	=2N4296: 500/350V, hFE=25...75		22a	TO-66			BUW 40A, B, BUX 84, TIP 50, 2N4240, ++
2 N 4299		Si-N	=2N4296: 500/350V, hFE=50...150		22a	TO-66			BUW 40A, B, BUX 84, TIP 50, 2N4240, ++
2 N 4300	USA, Tix	Si-N	LFS P, 100/80V, 2/4A, 15W(Tc=100°), >30MHz		2a	TO-5			BUX 49, BUY 41, 25C1860
2 N 4301	USA, Tix	Si-N	S P, 100/80V, 10/20A, 50W(Tc=100°), >40MHz		49m	TO-61			2N5288...89, 2N5542
2 N 4302	USA, Mic, Nsc	N-FET	Uni, In, 30V, Idss>0.5mA, Up<4V		8b	TO-106			BFS 70, 2N3821, 2N4220, 2SK104, 2SK301
2 N 4303	USA, Mic, Nsc	N-FET	Uni, In, 30V, Idss>4mA, Up<6V		8b	TO-106			BFS 80, BFW 11, 2N4416, 2N5362, 2N5245
2 N 4304	USA, Mic, Nsc	N-FET	Uni, In, 30V, Idss>0.5mA, Up<10V		8b	TO-106			2N3365
2 N 4305	USA, Tix	Si-N	LFS, 120/80V, 5A, 1.5W, <140/400ns, hFE=50...150		2a	TO-5			BFT 34, BUX 34, BUY 80, 2N4895...97
2 N 4306		Si-N	=2N4305: 30W		=55				-
2 N 4307		Si-N	=2N4305: 100/60V		2a	TO-5			BFT 33, BUX 34, BUY 80, 2N4895...97
2 N 4308		Si-N	=2N4307: 30W		=55				-
2 N 4309		Si-N	=2N4305: hFE=40...120		2a	TO-5			BFT 34, BUX 34, BUY 80, 2N4895...97
2 N 4310		Si-N	=2N4309: 30W		=55				-
2 N 4311		Si-N	=2N4305: 100/60V, hFE=40...120		2a	TO-5			BFT 33, BUX 34, BUY 80, 2N4895...97
2 N 4312		Si-N	=2N4311: 30W		=55				-
2 N 4313	USA, Mic, Nsc	Si-P	S, 12/12V, 0.1A, 0.2W, <25/35ns		8a	TO-106			BSX 36
2 N 4314	USA, Nsc, Rca	Si-P	LFS, 90/65V, 1A, 1W, >60MHz		2a	TO-5			BCX 60, BSS 17, BSV 17, 2N3634...37
2 N 4315	Amp	Si-N	Dual, 30V, 0.05A, 0.4W, >100MHz		TO-77	(CBE-FBC-)			2N3409...11
2 N 4316	Fch, Ssi	50Hz-Thy	100V, 8A(Tc=85°), 9.2A=, Igt/Ih<15/<25mA		22a	TO-66	(TAG 626-600) ⁵	17e	BStC0506, TAG 671-100, TAG 676-100
2 N 4317		50Hz-Thy	=2N4316: 200V		22a	TO-66	(TAG 626-600) ⁵	17e	BStC0513, TAG 671-200, TAG 676-200
2 N 4318		50Hz-Thy	=2N4316: 300V		22a	TO-66	(TAG 626-600) ⁵	17e	BStC0526, TAG 671-300, TAG 676-300